

# HUBER+SUHNER® DATA SHEET

## Within Series Adaptor: 46\_N-50-0-1/133\_U



### Description

T-adaptor, 3 jacks  
N jack (female) / N jack (female)  
Interface standard  
Series N - IEC 61169-16\_MIL-STD-348A/304\_CECC 22210

### Technical Data

#### Electrical Data

Impedance 50 Ω  
Interface frequency max. 11 GHz

#### Mechanical Data

Number of matings 500  
Weight 0.0568 kg

#### Environmental Data

Operating Temperature -65 °C to 165 °C  
2002/95/EC (RoHS) compliant

#### Material Data

##### Piece Parts

##### Interface - N jack (female)

	Material
Centre contact	Copper Beryllium Alloy
Outer contact	Brass
Body	Brass
Insulator	PFA / PTFE

##### Interface - N jack (female)

	Material
Centre contact	Copper Beryllium Alloy
Outer contact	Brass
Body	Brass
Insulator	PFA / PTFE

##### Surface Plating

Gold Plating (without Nickel underplating)  
SUCOPLATE (R) Plating  
SUCOPLATE (R) Plating

Gold Plating (without Nickel underplating)  
SUCOPLATE (R) Plating  
SUCOPLATE (R) Plating

#### Related Documents

Outline drawing DOU-00013510

#### Ordering Information

Single package 46\_N-50-0-1/133\_UE



HUBER+SUHNER is certified according to ISO 9001 and ISO 14001

#### WAIVER!

It is exclusively in written agreements that we provide our customers with warrants and representations as to the technical contained specifications and/or the fitness for any particular purpose. The facts and figures herein are carefully compiled to the best of our knowledge, but they are intended for general informational purposes only.



**HUBER+SUHNER AG**  
RF Technology  
9100 Herisau, Switzerland  
Phone +41 (0)71 353 41 11  
Fax +41 (0)71 353 45 90  
www.hubersuhner.com

**HUBER+SUHNER – Excellence in Connectivity Solutions**

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [RF Connectors / Coaxial Connectors](#) category:*

*Click to view products by [Huber & Suhner](#) manufacturer:*

Other Similar products are found below :

[R125315120](#) [8915-1511-000](#) [89674-0827](#) [5916-1103-603](#) [0106-001-000](#) [6-0001-3](#) [6001-7071-019](#) [6002-7051-003](#) [6002-7551-202](#) [6059674-1](#) [619550-1](#) [630059-000](#) [M39012/25-0021](#) [M39012/79-3008](#) [M39030/3-01N](#) [M39030/3-03N](#) [M3933/25-29N](#) [M3933/25-36N](#) [6500-7071-046](#) [6501-1071-002](#) [M83723/72W24576](#) [M83723/72W2457N](#) [6769](#) [CX050L2AQ](#) [7002-1541-010](#) [7003-1572-002](#) [7004-1512-000](#) [7009-1511-004](#) [7010-1511-000](#) [7029-1511-060](#) [7101-1541-010](#) [7101-1571-002](#) [7105-1521-002](#) [7145-1521-002](#) [7209-1511-011](#) [7210-1511-012](#) [7210-1511-015](#) [7210-1511-019](#) [7210-1511-040](#) [7225-1512-050](#) [7242-1511-000](#) [73137-5015](#) [73251-0111](#) [73251-0672](#) [73276-1501](#) [73366-0013](#) [73404-2300](#) [73413-6080](#) [734151610](#) [73415-5721](#)