



General ordering data

Order No.	9019180000
Part designation	H2,5/24D BL
Version	Wire-end ferrule, 2.5 mm ² , 18 mm, Colour code: DIN, Blue
EAN	4008190101145
Qty.	500 pc(s).

Technical data

Length	24 mm
Width	4.7 mm
Height	4.7 mm

Product data

Conductor rated cross-section	2.5 mm ²
AWG	14
Total length (L1)	24 mm
Contact surface length (L2)	18 mm
Contact surface diameter (D1)	2.2 mm
Collar diameter (D2)	4.2 mm
Metal sleeve thickness (S1)	0.15 mm
Plastic collar thickness (S2)	0.25 mm

Approvals

Approvals institutes



Classifications

ETIM 2.0	EC000005
ETIM 3.0	EC000005
eClass 4.1	27-06-07-01
eClass 5.0	27-40-02-01
eClass 5.1	27-40-02-01

Classifications

Similar products

Order No.	Part designation	Version
9019160000	H2,5/14D BL	Wire-end ferrule, 2.5 mm ² , 8 mm, Colour code: DIN, Blue
9021070000	H2,5/14T GR	Wire-end ferrule, 2.5 mm ² , 8 mm, Colour code: Miscellaneous, grey
9019170000	H2,5/18D BL	Wire-end ferrule, 2.5 mm ² , 12 mm, Colour code: DIN, Blue
9021080000	H2,5/18T GR	Wire-end ferrule, 2.5 mm ² , 12 mm, Colour code: Miscellaneous, grey
9021090000	H2,5/24T GR	Wire-end ferrule, 2.5 mm ² , 18 mm, Colour code: Miscellaneous, grey

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Terminals](#) category:

Click to view products by [Weidmuller](#) manufacturer:

Other Similar products are found below :

[HT-13-10](#) [71M-250-32-NB](#) [01-2065-1-0216](#) [00581P0075](#) [M10-10RX](#) [M10BCK](#) [60205-1](#) [604200-1](#) [60598-1-CUT-TAPE](#) [60617-1-C](#) [60873-1](#) [M14-516R/SK](#) [M14-6RSX](#) [M18-10FLX](#) [M18-8FBX](#) [M18-8R/LX](#) [M18BCK](#) [61314-6-C](#) [61-S](#) [61-SN-A](#) [62-NBM-A](#) [63-S](#) [640179-1](#) [640917-2-CUT-TAPE](#) [6501550002](#) [66107-2-C](#) [66107-4-C](#) [696683-1](#) [696834-1](#) [696861-1](#) [696931-1](#) [696999-1](#) [M8-516RK](#) [M86700006](#) [MA250DMFMX-A](#) [701-2007](#) [701-2307](#) [701-7761-03](#) [70F-110-32-PB](#) [718-N-A](#) [71M-187-20-NBL](#) [71M-250-32-NBL](#) [72F-187-20-NBL](#) [72M-250-32-NBL](#) [7310](#) [73F-250-32](#) [73F-250-32-NBL](#) [73F-250-32-NL](#) [F14-10C](#) [F-1M](#)