



#### General ordering data

Order No.	9037570000
Part designation	H10,0/26D ZH R
Version	Wire end ferrule, 10 mm <sup>2</sup> , 12 mm, Colour code: DIN, red
EAN	4008190493141
Qty.	100 pc(s).

#### Technical data

Length	26 mm
Width	8.4 mm
Height	14.2 mm

#### Product data

Conductor rated cross-section	10 mm <sup>2</sup>
AWG	7
Total length (L1)	26 mm
Contact surface length (L2)	12 mm
Collar height (A)	13.4 mm
Collar width (B)	7.6 mm
Contact surface diameter (D1)	5.8 mm
Metal sleeve thickness (S1)	0.2 mm
Plastic collar thickness (S2)	0.5 mm

#### Approvals

Approvals institutes



#### Classifications

ETIM 2.0	EC000005
ETIM 3.0	EC000005
eClass 4.1	27-06-07-01
eClass 5.0	27-40-02-01

### Classifications

eClass 5.1

27-40-02-01

### Similar products

Order No.	Part designation	Version
9018860000	H10/24S ZH EB	Wire end ferrule, 10 mm <sup>2</sup> , 12 mm, Colour code: Weidmüller, Ivory
9018880000	H10,0/24DS ZH R	Wire end ferrule, 10 mm <sup>2</sup> , 12 mm, Colour code: DIN, red
9037340000	H10,0/26 ZH EB	Wire end ferrule, 10 mm <sup>2</sup> , 12 mm, Colour code: Weidmüller, Ivory
9037710000	H10,0/26T ZH BR	Wire end ferrule, 10 mm <sup>2</sup> , 12 mm, Colour code: Miscellaneous, brown
9037350000	H10,0/30 ZH EB	Wire end ferrule, 10 mm <sup>2</sup> , 18 mm, Colour code: Weidmüller, Ivory
9018870000	H10/30S ZH EB	Wire end ferrule, 10 mm <sup>2</sup> , 18 mm, Colour code: Weidmüller, Ivory
9018890000	H10/30DS ZH R	Wire end ferrule, 10 mm <sup>2</sup> , 18 mm, Colour code: DIN, red
9037580000	H10,0/30D ZH R	Wire end ferrule, 10 mm <sup>2</sup> , 18 mm, Colour code: DIN, red
9037720000	H10,0/30T ZH BR	Wire end ferrule, 10 mm <sup>2</sup> , 18 mm, Colour code: Miscellaneous, brown

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Terminals](#) category:*

*Click to view products by [Weidmuller](#) manufacturer:*

Other Similar products are found below :

[HT-13-10](#) [71M-250-32-NB](#) [01-2065-1-0216](#) [00581P0075](#) [M10-10RX](#) [M10BCK](#) [60205-1](#) [604200-1](#) [60598-1-CUT-TAPE](#) [60617-1-C](#) [60873-1](#) [M14-516R/SK](#) [M14-6RSX](#) [M18-10FLX](#) [M18-8FBX](#) [M18-8R/LX](#) [M18BCK](#) [61314-6-C](#) [61-S](#) [61-SN-A](#) [62-NBM-A](#) [63-S](#) [640179-1](#) [640917-2-CUT-TAPE](#) [6501550002](#) [66107-2-C](#) [66107-4-C](#) [696683-1](#) [696834-1](#) [696861-1](#) [696931-1](#) [696999-1](#) [M8-516RK](#) [M86700006](#) [MA250DMFMX-A](#) [701-2007](#) [701-2307](#) [701-7761-03](#) [70F-110-32-PB](#) [718-N-A](#) [71M-187-20-NBL](#) [71M-250-32-NBL](#) [72F-187-20-NBL](#) [72M-250-32-NBL](#) [7310](#) [73F-250-32](#) [73F-250-32-NBL](#) [73F-250-32-NL](#) [F14-10C](#) [F-1M](#)