



## 308N100

**308 Series Industrial Potentiometer, Conductive Plastic Element, Solder Hook Terminals, 0.5 W Power Rating, 100 Ohm Resistance Value**

*Representative photograph, actual product appearance may vary.*

*Due to regional agency approval requirements, some products may not be available in your area. Please contact your regional Honeywell office regarding your product of choice.*

### Features

- Compact - 12,7 mm [0.5 in] modular size
- Robust nickel-plated brass shaft and bushings
- Conductive plastic element
- Linear taper
- Solder hook terminals

### Typical Applications

- Manual controls
- Medical equipment
- Telecommunications

### Description

The 308 Series is a low cost, conductive plastic, potentiometer. It offers a 1/2 watt power rating and a metal shaft and bushing. PC and solder hook style terminals available.

## 308N100

**308 Series Industrial Potentiometer, Conductive Plastic Element, Solder Hook Terminals, 0.5 W Power Rating, 100 Ohm Resistance Value**

Product Specifications	
Potentiometer Type	Industrial
Element Type	Conductive Plastic
Terminal Type	Solder Hook
Power Rating	0.5 W
Resistance Value	100 Ohm
Resistance Tolerance	± 10 %
Linearity	± 5 %
Bushing Thread	6,35 mm [0.25 in] x 32 NEF-2A
Bushing length	6,35 mm [0.25 in]
Bushing Type	Standard
Shaft Diameter	3,18 mm [0.125 in]
Shaft length	19,05 mm [0.75 in]
Shaft Ending	Slotted
Body	12.7 mm [0.5 in] square, ± 0.79 mm [0.031 in]
Electrical Taper	Linear
Operating Temperature	-40 °C to 120 °C [-40 °F to 248 °F]
Working Voltage (Max.)	350 V
Rotational Life	50000 cycles
Mechanical Rotation	295°
Availability	Global
Series Name	308 Series
UNSPSC Code	4111363300
UNSPSC Commodity	4111363300 Potentiometers

# Honeywell

## 308N100

308 Series Industrial Potentiometer, Conductive Plastic Element, Solder Hook Terminals, 0.5 W Power Rating, 100 Ohm Resistance Value

[\[Dimensions\]](#)

# Honeywell

# 308N100

308 Series Industrial Potentiometer, Conductive Plastic Element, Solder Hook Terminals, 0.5 W Power Rating, 100 Ohm Resistance Value

## **WARNING**

### **PERSONAL INJURY**

DO NOT USE these products as safety or emergency stop devices, or in any other application where failure of the product could result in personal injury.

**Failure to comply with these instructions could result in death or serious injury.**

## **WARNING**

### **MISUSE OF DOCUMENTATION**

- The information presented in this product sheet (or catalog) is for reference only. DO NOT USE this document as product installation information.
- Complete installation, operation and maintenance information is provided in the instructions supplied with each product.

**Failure to comply with these instructions could result in death or serious injury.**

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [honeywell](#) manufacturer:*

Other Similar products are found below :

[14CE2-2](#) [91MCE2-S5](#) [GLLA06A1B](#) [3600080010001](#) [58C1-25](#) [58C1-3K](#) [5ML1-E1](#) [5SE1-12](#) [602HE1-6](#) [604HE223-6B](#) [61CX11-D01](#)  
[M3050A13](#) [64AT22-3D](#) [66AT23-7](#) [6HM7-6](#) [MA215HT-96](#) [6PA104](#) [6PA148-E6](#) [701PB580](#) [727033](#) [EXD-AR20](#) [MD3211Q16](#) [76054-](#)  
[00000700-01](#) [76061-00000015-15](#) [76061-B00000020-01](#) [76078-00000350-01](#) [76078-B00000400-01](#) [76584-M00000100-24](#) [F78EA502](#)  
[F78SA102-B1](#) [77028-00001500-01](#) [77050-04000400-01](#) [78148-B00001000-01](#) [78408-00000100-01](#) [78410-00000400-01](#) [78SF2B103](#) [7HM5](#)  
[FE7C-FRC6S-M](#) [FEF-PAD6-ML2](#) [FE-MLS9C](#) [FFS-20-03](#) [81808-B00000150-14](#) [ML-1155](#) [ML-1376](#) [82000-11](#) [MLH010BST01A](#)  
[MLH025BGC13B](#) [MLH02KPSG06A](#) [MLH03KPSL01C](#) [MLH250BSL01B](#)