
Item no.: 2001-1204
Product description: 2-CONDUCTOR THROUGH TERMINAL BLOCK SUITABLE FOR EX E APPLICATIONS SUITABLE FOR EX I APPLICATIONS



Produkt kann von Bild abweichen / product may differ

Packing unit 100 pieces

RoHS compliant

Current intensity EN	24 A
Product group	22 (TOPJOB S RAIL-MOUNTED TERMINAL BLOCKS)
Cross section [mm ²]	0.25 - 1.5 mm ²
Cross section [AWG]	22 - 14 AWG
Connection method	CAGE CLAMP®S Connection
Cross section [mm ²]	0.25 - 2.5 mm ²
Cross section [AWG]	22 - 14 AWG
Wiring method	e+f
Connection method	CAGE CLAMP®S Connection
Measured voltage EN	800 V
Measured shock voltage	8 kV
Pollution degree	3
Current intensity EN	18 A
Weight	3.484 g
Color	blue
Wiring type	Front-entry
No. of connection Points	2

No. of potentials	1
Height	33 mm
Height	1.299 in
Width	4.2 mm
Width	0.165 in



Depth	48.5 mm
Depth	1.909 in
Strip length from	9 mm
Strip length to	11 mm
Strip length	0.39 in
Customs Tariff No.	85369010
Country of Origin	Deutschland
Mounting	TS 35



Item no.	Admission office	Approval no.	Voltage [V]	Current [A]	Cross section [mm ²]
2001-1204	ABS	05-HG476175/3-PDA	800	18	0,5-2,5
2001-1204	AEX	E185892	550	15	22-14
2001-1204	CCA	NL6386	800	18/24	0,5-1,5/2,5
2001-1204	CSA	154112-1645434	600	15	22-14
2001-1204	DNV	E-10423	800	24	2,5
2001-1204	GL	26187-05HH	800	18	0,25-1,5
2001-1204	KEMA	2116586.01	800	18	0,5-2,5
2001-1204	LR	91/20112(E6)	800	18	0,25 -2,5
2001-1204	PRS	TE/1718/880590/08	800	18	0,5-2,5
2001-1204	PTB	IECExPTB05.0034U	550	16	0,5-2,5
2001-1204	PTB	PTB05ATEX094U	550	16	0,5-2,5
2001-1204	RosTest	8189158	550	16	0,5-2,5
2001-1204	UR	E45172	600	15	22-14

Sorting criteria: admission office - approval number

© WAGO Kontakttechnik GmbH & Co. KG

Specifications are subject to changes and errors may be expected

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [wago manufacturer](#):

Other Similar products are found below :

[750-460](#) [231-118/026-000](#) [231-303/026-000](#) [231-620/019-000](#) [257-403](#) [280-438](#) [280-831](#) [284-624](#) [210-111](#) [231-303/037-000](#) [231-446/001-000_NR](#) [232-216/026-000](#) [234-510](#) [264-726](#) [280-339](#) [0283-0671](#) [830-800/000-305](#) [750-512](#) [750-455](#) [51251782](#) [286-312](#) [713-1428/107-000](#) [731-138/048-000](#) [750-459](#) [750-517](#) [750-602](#) [793-3505](#) [826-172](#) [859-304](#) [280-335](#) [231-535/001-000](#) [2604-1105](#) [2604-1106](#) [2604-1504](#) [2606-1103/020-000](#) [2624-1103](#) [2626-3103/020-000](#) [821-104](#) [713-1107](#) [852-1411](#) [2106-1307](#) [2116-5307](#) [832-1205](#) [832-3604](#) [2009-110](#) [281-512/281-501](#) [286-336](#) [750-421](#) [750-838](#) [753-559](#)