







TOPJOB® S

Through/Ground Conductor/Shield and Ex Terminal Blocks 2.5 (4) mm²

2002 Series

0.25 ... 2.5 (4) mm ² ① 800 V/8 kV/3 ② I _N 24 A (32 A)	AWG 22 ... 12 600 V, 20 A ④ 600 V, 20 A ⑥	0.25 ... 2.5 (4) mm ² ① 800 V/8 kV/3 ② I _N 24 A (32 A)	AWG 22 ... 12 600 V, 20 A ④ 600 V, 20 A ⑥	0.25 ... 2.5 (4) mm ² ① 800 V/8 kV/3 ② I _N 24 A (32 A)	AWG 22 ... 12 600 V, 20 A ④ 600 V, 20 A ⑥
Terminal block width 5.2 mm / 0.205 in.  10 ... 12 mm / 0.43 in. ③		Terminal block width 5.2 mm / 0.205 in.  10 ... 12 mm / 0.43 in. ③		Terminal block width 5.2 mm / 0.205 in.  10 ... 12 mm / 0.43 in. ③	



Item No.	Pack. Unit	Item No.	Pack. Unit	Item No.	Pack. Unit
2-conductor through terminal block		3-conductor through terminal block		4-conductor through terminal block	
gray ⑤ 2002-1201 ⑤ 100		gray ⑤ 2002-1301 ⑤ 100		gray ⑤ 2002-1401 ⑤ 100	
blue ⑤ 2002-1204 ④ ⑤ 100		blue ⑤ 2002-1304 ④ ⑤ 100		blue ⑤ 2002-1404 ④ ⑤ 100	
orange ⑤ 2002-1202 ⑤ 100		orange ⑤ 2002-1302 ⑤ 100		orange ⑤ 2002-1402 ⑤ 100	
red ⑤ 2002-1203 ⑤ 100		red ⑤ 2002-1303 ⑤ 100		red ⑤ 2002-1403 ⑤ 100	
black ⑤ 2002-1205 ⑤ 100		black ⑤ 2002-1305 ⑤ 100		black ⑤ 2002-1405 ⑤ 100	
yellow ⑤ 2002-1206 ⑤ 100		yellow ⑤ 2002-1306 ⑤ 100		yellow ⑤ 2002-1406 ⑤ 100	
2-conductor ground terminal block		3-conductor ground terminal block		4-conductor ground terminal block	
green-yellow ⑤ 2002-1207 ⑤ 100		green-yellow ⑤ 2002-1307 ⑤ 100		green-yellow ⑤ 2002-1407 ⑤ 100	
		3-conductor shield terminal block		4-conductor shield terminal block	
		white 2002-1308 100		white 2002-1408 100	
Other terminal blocks with the same profile:		Other terminal blocks with the same profile:		Other terminal blocks with the same profile:	
Diode 2002-1211/1000-411 Page 82		Diode 2002-1311/1000-411 Page 82		Diode 2002-1411/1000-411 Page 82	
		LED 2002-1321/1000-434 Page 82		LED 2002-1421/1000-434 Page 82	
				Double-potential 2002-1441 Page 15	
Item-Specific Accessories		Item-Specific Accessories		Item-Specific Accessories	
End and intermediate plate, 0.8 mm thick		End and intermediate plate, 0.8 mm thick		End and intermediate plate, 0.8 mm thick	
orange 2002-1292 100 (4x25)		orange 2002-1392 100 (4x25)		orange 2002-1492 100 (4x25)	
gray 2002-1291 100 (4x25)		gray 2002-1391 100 (4x25)		gray 2002-1491 100 (4x25)	
Separator, oversized, 2 mm thick		Separator, oversized, 2 mm thick		Separator, oversized, 2 mm thick	
orange 2002-1294 100 (4x25)		orange 2002-1394 100 (4x25)		orange 2002-1494 100 (4x25)	
gray 2002-1293 100 (4x25)		gray 2002-1393 100 (4x25)		gray 2002-1493 100 (4x25)	
Ex e/Ex i separator, orange, 3 mm thick		Ex e/Ex i separator, orange, 3 mm thick		Ex e/Ex i separator, orange, 3 mm thick	
90 mm 209-190 50 (2x25)		120 mm 209-191 50 (2x25)		120 mm 209-191 50 (2x25)	

2002 Series Accessories

Appropriate marking systems: WMB/Marking strips/WMB Inline (see Section 13)

Insulation stop,	Push-in type jumper bar, insulated,	Push-in type jumper bar, insulated,
5 pcs/strip, 0.25 ... 0.5 mm ² light gray 2002-171 200 (8x25)	⑥ I _N 25 A, light gray 2-way 2002-402 200 (8x25) 3-way 2002-403 200 (8x25) 4-way 2002-404 200 (8x25) 5-way 2002-405 100 (4x25) 6-way 2002-406 100 (4x25) 7-way 2002-407 100 (4x25) 8-way 2002-408 100 (4x25) 9-way 2002-409 100 (4x25) 10-way 2002-410 100 (4x25)	I _N 25 A, light gray from 1 to 3 2002-433 200 (8x25) from 1 to 4 2002-434 200 (8x25) from 1 to 5 2002-435 100 (4x25) from 1 to 6 2002-436 100 (4x25) from 1 to 7 2002-437 100 (4x25) from 1 to 8 2002-438 100 (4x25) from 1 to 9 2002-439 100 (4x25) from 1 to 10 2002-440 100 (4x25)
Insulation stop, 5 pcs/strip, 0.75 ... 1 mm ² dark gray 2002-172 200 (8x25)		
Protective warning marker, with high-voltage symbol, black, for 5 terminal blocks yellow 2002-115 100 (4x25)		

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [wago manufacturer](#):

Other Similar products are found below :

[750-460](#) [231-118/026-000](#) [231-303/026-000](#) [231-620/019-000](#) [257-403](#) [280-438](#) [280-831](#) [284-624](#) [210-111](#) [231-303/037-000](#) [231-446/001-000_NR](#) [232-216/026-000](#) [234-510](#) [264-726](#) [280-339](#) [0283-0671](#) [830-800/000-305](#) [750-512](#) [750-455](#) [51251782](#) [286-312](#) [713-1428/107-000](#) [731-138/048-000](#) [750-459](#) [750-517](#) [750-602](#) [793-3505](#) [826-172](#) [859-304](#) [280-335](#) [231-535/001-000](#) [2604-1105](#) [2604-1106](#) [2604-1504](#) [2606-1103/020-000](#) [2624-1103](#) [2626-3103/020-000](#) [821-104](#) [713-1107](#) [852-1411](#) [2106-1307](#) [2116-5307](#) [832-1205](#) [832-3604](#) [2009-110](#) [281-512/281-501](#) [286-336](#) [750-421](#) [750-838](#) [753-559](#)