313 2444

MINIATURLAMPEN / MINIATURE LAMPS

No est	and the Commence of the Commen				Sockel / Base; BA	Pase: BA 9s / E 10-13	
T - 10 x 28 (Ø 10 mm)		·	Мав	stab: 1:1	*		
			scale	1:1	0 10 max	0246	
					28 max.	0246	
Spann⊔ng Voltage (V)	Stromstärke Current (mA) / (W)	Lichtausbeute Light outpul	Lebensdauer Lifetime (h) AC	Wendelaufbau Filament	0242	28 max.	
					EBT Nr. / Intern. Nr	. EBT Nr. / Intern. Nr.	
4	100	0,14	5.000	C-2R	_ / _	02461401 / 432	
5 5	50 90	0,08 0,25	1.000 750	C-2R C-2R	02421600 / 438 02421601 / 1850	02461601 / 439	
6 6	75 •100	0,32 0,20	100 5.000	C-6 C-2R	02422201 / 1140 02422405 / —	_ / _	
6 6	1,2 W 2 W	0,30 0,50	15.000 15.000	C-2R C-2R	02422601 / 1212 02423000 / ——	02462605 / —— 02462805 / ——	
6,3 6,3 6,3	150 150 250	0,33 0,52	15.000 3.000	C-2R C-2R	02423401 / 755 02423601 / 47	/ 02463301 / 40	
6,5	300	0,90	4.000	C-2R C-2R	02423901 / 44 02425001 / 504	02463801 / 46	
8	300	1,15	4.000	C-2R	02426001 / 528		
10	138	0,88	300	C-2V	02426501 / 1280	_ / _	
12 12	1,2 100	0,25 0,40	10.000 5.000	C-2F C-2F	02426612 / 1221	/	
12 12	138 3 W	0,88 1,00	3.000 2.000	C-2V C-2V	02427101 / 643 02427200 / 	02466605 / —— 02467001 / 1309 02467200 / ——	
14 14	80	0,31	7.500	C-2F	02427501 / 756		
14	330	1,40 2,00	3.000	C-2V C-2F	02427701 / 1815 02428101 / 1893	_ / _	
24 24	1,2 50	0,25 0,32	10.000 5.000	C-2F C-2F	02428801 / 1210 02428901 / 568	02458001 / 755	
24 /28	2 W	0,50 0,62	10.000 7.500	C-2F C-2F	02428903 / 1201 02429101 / —	02468901 / 592 02469101 / 22	
24	3 W	0,95	3.000	C-2F	02429301 / 600	02469301 / 599	

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for lux manufacturer:

Other Similar products are found below:

BS239 BS233 N9951189 BS460 6240-99-995-1183 BS207 BS448 6240-99-995-1294 6240-99-995-9233 BS247 BS382 N9951903 BS245 6839*M BS150 6240-99-995-1233 G987-5