



Digital Storage Oscilloscope



72-8705A



72-8710A

Specification

	72-8705A	72-8710A
Channels	2	
Bandwidth	50MHz	100MHz
Sample Rate	1Gs/s	
Rise Time	≤7ns	≤3.5ns
Memory Depth	25kpts	
Waveform Acquisition Rate	≥2000wfms/s	
Vertical Sensitivity(V/div)	1mV/div~20V/div	
Timebase Range(s/div)	2ns/div~50s/div	
Storage	Setup,Wave,Bitmap	
Trigger Modes	Edge, Pluse, Video,Slope,Alternate	
Interface	USB OTG	

General Characteristic

Power	: 100 - 240V AC, 45 - 440Hz
Display	: 7 Inches 64K Colour TFT LCD, 800 × 480
Product Colour	: White and Grey
Product Net Weight	: 2.2kg
Product Size (W×H×D)	: 306mm × 147mm × 122mm
Standard Accessories	: Probe×2 (1×,10× switchable), Power Cord , USB Cable, PC Software CD
Optional Accessories	: LAN Port

Part Number Table

Description	Part Number
Digital Storage Oscilloscope	72-8710A, 72-8705A

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.



X-ON Electronics

Authorized Distributor

Click to view similar products for [Tenma manufacturer](#).

Other Similar products are found below :

[2110130UKEU](#) [2110140](#) [2110142](#) [2110144](#) [2110146](#) [2110148](#) [2110150](#) [2110152](#)
[2110154](#) [2110156](#) [2110158](#) [2110160](#) [2110162](#) [2110164](#) [2110168](#) [2110170](#) [211040](#)
[211041](#) [211042](#) [211045](#) [211046](#) [211047](#) [211050](#) [2110562](#) [2110563](#)