



# Mini Mylar Cone Loudspeaker **pro-SIGNAL**



## Specifications:

Rated Impedance	: 32Ω ±15%Ω
Power (Nominal)	: 0.25W
Power (Max)	: 0.5W
Rated Resonant Frequency	: 500Hz ±25Hz
Rated Frequency Range (f)	: 0 to 5,500Hz
Rated Sound Output	: 85 ±3dB 0.5W / 0.5m 92 ±3dB 0.1W / 0.1m
Cone Material	: Mylar
Magnet Material : Nd-Fe-B	: ø12.5 × 1.5
Housing Material	: Matel
Operating Temperature	: -20°C to +60°C
Storage Temperature	: -30°C to +70°C
Weight	: 12g
External Dia	: 45mm
External Height	: 5.8mm
External Width	: 45mm
Sound Level Distance	: 10cm



Dimensions: Millimetres

## Part Number Table

Description	Part Number
Loudspeaker, Mini, Mylar Cone Speaker Transducer	ABS-209-RC

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. pro-SIGNAL is the registered trademark of the Group. © Premier Farnell plc 2012.

[www.element14.com](http://www.element14.com)  
[www.farnell.com](http://www.farnell.com)  
[www.newark.com](http://www.newark.com)  
[www.cpc.co.uk](http://www.cpc.co.uk)

**pro-SIGNAL**

# X-ON Electronics

Authorized Distributor

*Click to view similar products for [Pro Signal](#) manufacturer.*

Other Similar products are found below :

[11998795](#) [11998870](#) [11998871](#) [11W3S61106IN](#) [1260B](#) [2413485](#) [2413486](#) [2415620](#)  
[2415621](#) [2415622](#) [2415623](#) [2415624](#) [2415625](#) [2415626](#) [2415627](#) [2415628](#) [271450](#)  
[275915](#) [277942](#) [278076](#) [278155](#) [278159](#) [278160](#) [278162](#) [278174](#)