

Male headers soldering technique

☐ 0.635 mm, standard

art. no.	dim. [mm]			art. no.	dim. [mm]		
	A	B	C		A	B	C
SL 11 112 ...	11.20	3.00	5.40	SL 1 025 ...	11.20	2.60	5.80
SL 11 124 ...	12.40	3.00	6.60	SL 1 053 ...	13.90	5.80	5.30
SL 11 139 ...	13.90	3.00	8.10	SL 1 078 ...	16.40	5.80	7.80
SL 11 164 ...	16.40	3.00	10.60	SL 1 104 ...	19.00	5.80	10.40
SL 11 190 ...	19.00	3.00	13.20	SL 1 128 ...	21.40	5.80	12.80
SL 11 214 ...	21.40	3.00	15.60	SL 1 154 ...	24.00	5.80	15.40
SL 11 240 ...	24.00	3.00	18.20	SL 1 179 ...	26.50	5.80	17.90
SL 11 265 ...	26.50	3.00	20.70	SL 1 230 ...	31.60	5.80	23.00
SL 11 316 ...	31.60	3.00	25.80				
art. no.	dim. [mm]			art. no.	dim. [mm]		
	A	B	C		A	B	C
SL 22 112 ...	11.20	3.00	5.40	SL 2 025 ...	11.20	2.60	5.80
SL 22 124 ...	12.40	3.00	6.60	SL 2 053 ...	13.90	5.80	5.30
SL 22 139 ...	13.90	3.00	8.10	SL 2 078 ...	16.40	5.80	7.80
SL 22 164 ...	16.40	3.00	10.60	SL 2 104 ...	19.00	5.80	10.40
SL 22 190 ...	19.00	3.00	13.20	SL 2 128 ...	21.40	5.80	12.80
SL 22 214 ...	21.40	3.00	15.60	SL 2 154 ...	24.00	5.80	15.40
SL 22 240 ...	24.00	3.00	18.20	SL 2 179 ...	26.50	5.80	17.90
SL 22 265 ...	26.50	3.00	20.70	SL 2 230 ...	31.60	5.80	23.00
SL 22 316 ...	31.60	3.00	25.80				
<b>please indicate:</b>	<b>... no. of contacts</b>			<b>... surface</b>			
	one row 1-36			S = selective gold-plated			
	two rows 2-72			G = gold-plated			
				Z = tin-plated			

Every pin length is available on request.

PC connector design DIL → H 2  
 Female headers 2.54 solder → G 27  
 Technical data → G 73 - 76  
 Fem. head. 2.54 solder, put through → G 28

Female headers 2.54 SMD → G 41 - 44  
 Special male & female headers → G 18  
 High-prec. fem. headers 2.54 sold. → G 30 - 33  
 Bar magazine → G 20 - 21

Female headers 2.54 SMD → G 41 - 44  
 Special male & female headers → G 18  
 High-prec. fem. headers 2.54 sold. → G 30 - 33  
 Bar magazine → G 20 - 21

→ G 41 - 44  
 → G 18  
 → G 30 - 33  
 → G 20 - 21

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [FFC & FPC Connectors](#) category:*

*Click to view products by [Fisher](#) manufacturer:*

Other Similar products are found below :

[HFW11R-1STE1H1LF](#) [FH29B-100S-0.2SHW\(99\)](#) [FA5S008HP1](#) [FH29B-120S-0.2SHW\(99\)](#) [FH29B-80S-0.2SHW\(99\)](#) [FHS-16](#) [FPH-2022G](#)  
[52610-1075](#) [52610-1275](#) [52610-1934](#) [XF3M\(1\)-1415-1B-R100](#) [501864-3091-TR225](#) [0525594033](#) [086210010340800](#) [086222026001800](#)  
[52271-2869-CUT-TAPE](#) [62674-201121DLF](#) [62684-36210E9ALF](#) [52610-1675](#) [52746-1671-TR250](#) [10051922-2810EHLF](#) [6-520415-9](#)  
[BD021-09A-A1-0350-0200-0550-LD](#) [SFV6R-1STE9HLF](#) [XF3M-2915-1B-R100](#) [1658549-1](#) [62674-221121ALF](#) [46214008010800](#)  
[046298003000883](#) [151660622](#) [842-816-2630-035](#) [AYF530665TA](#) [AYF351525](#) [046296011930846+](#) [AYF352325A](#) [046254020000800+](#)  
[FH19C-13S-0.5SH\(99\)](#) [FH39J-51S-0.3SHW\(99\)](#) [AYF355125A](#) [AYF530365TA](#) [FH29B-44S-0.2SHW\(99\)](#) [SFW5R-2STAE9LF](#) [AYF351125A](#)  
[AYF350725A](#) [62684-502100AHLF](#) [FH39-61S-0.3SHW\(99\)](#) [AYF414035A](#) [10064555-172520HLF](#) [AYF212335A](#) [504754-2500](#)