

# 1 Modular Terminal Blocks with Fixing Flange or Snap-in Mounting Foot, Series 262

24 Side-entry

0.08 – 4 mm<sup>2</sup> | AWG 28 – 12  
630 V/8 kV/3 ① | 300/600 V, 20/5 A ②  
24 A | 300/600 V, 20/5 A ③

Terminal block width 7 mm / 0.276 in  
9 – 10 mm / 0.37 in

\* VDE IEC CCA ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿

2 x 0.08 – 4 mm<sup>2</sup> | 2 x AWG 28 – 12  
630 V/8 kV/3 ① | 300/600 V, 20/5 A ②  
32 A | 300/600 V, 20/5 A ③




Terminal block width 12 mm / 0.472 in  
9 – 10 mm / 0.37 in

\* VDE IEC CCA ④ ⑤ ⑥ ⑦ ⑧ ⑨ ⑩ ⑪ ⑫ ⑬ ⑭ ⑮ ⑯ ⑰ ⑱ ⑲ ⑳ ㉑ ㉒ ㉓ ㉔ ㉕ ㉖ ㉗ ㉘ ㉙ ㉚ ㉛ ㉜ ㉝ ㉞ ㉟ ㊱ ㊲ ㊳ ㊴ ㊵ ㊶ ㊷ ㊸ ㊹ ㊺ ㊻ ㊼ ㊽ ㊾ ㊿










① 630 V = rated voltage  
8 kV = rated surge voltage  
3 = pollution degree  
(see also section 10)

② Suitable for EEx i applications



Description	Color	Item-No.	Pack.-unit pcs	Color	Item-No.	Pack.-unit pcs
 <p><b>Terminal blocks with fixing flange</b>, for screw fixing or similar methods, fixing hole diameter 3.2 mm (with mounting adapter 209-123 also for DIN 35 rail)</p>	<b>2-conductor terminal blocks</b>			<b>4-conductor terminal blocks</b>		
	grey	<b>262-301</b>	100 (2 x 50)	grey	<b>262-331</b>	100 (2 x 50)
	blue	<b>262-304</b> ①	100 (2 x 50)	blue	<b>262-334</b> ①	100 (2 x 50)
	orange	<b>262-306</b>	100 (2 x 50)	orange	<b>262-336</b>	100 (2 x 50)
	green-yellow	<b>262-307</b>	100 (2 x 50)	green-yellow	<b>262-337</b>	100 (2 x 50)
 <p><b>Terminal blocks with snap-in mounting foot</b>, for plate thickness 0.6 – 1.2 mm, fixing hole diameter 3.5 mm (fits aluminum rail 210-154 or with mounting adapter 209-120 for DIN 35 rail)</p>	<b>2-conductor terminal blocks</b>			<b>4-conductor terminal blocks</b>		
	grey	<b>262-311</b>	100 (2 x 50)	grey	<b>262-341</b>	100 (2 x 50)
	blue	<b>262-314</b> ①	100 (2 x 50)	blue	<b>262-344</b> ①	100 (2 x 50)
	orange	<b>262-316</b>	100 (2 x 50)	orange	<b>262-346</b>	100 (2 x 50)
	green-yellow	<b>262-317</b>	100 (2 x 50)	green-yellow	<b>262-347</b>	100 (2 x 50)
 <p><b>End terminal block</b> ③, without fixing foot, for terminal strips with snap-in mounting feet (see dimensioned drawings on page 1.25.)</p>	<b>2-conductor terminal blocks</b>			<b>4-conductor terminal blocks</b>		
	grey	<b>262-321</b>	100 (2 x 50)	grey	<b>262-351</b>	100 (2 x 50)
	blue	<b>262-324</b> ①	100 (2 x 50)	blue	<b>262-354</b> ①	100 (2 x 50)
	orange	<b>262-326</b>	100 (2 x 50)	orange	<b>262-356</b>	100 (2 x 50)
	green-yellow	<b>262-327</b>	100 (2 x 50)	green-yellow	<b>262-357</b>	100 (2 x 50)

## Accessories for modular terminal blocks and terminal strips (Marking accessories see section 9.)

 <p><b>End plate with fixing flange</b></p>	grey	<b>262-361</b>	50	grey	<b>262-361</b>	50
 <p><b>End plate with snap-in mounting foot</b></p>	grey	<b>262-371</b>	50	grey	<b>262-371</b>	50
 <p><b>Comb type jumper bar</b>, insulated, 2-way</p>	I <sub>N</sub> 16 A grey	<b>262-402</b>	25	I <sub>N</sub> 16 A grey	<b>262-402</b>	25
 <p><b>Operating tool</b>, insulated, for connecting the comb type jumper bar</p>	2-way	<b>209-132</b>	1	2-way	<b>209-132</b>	1
 <p><b>Aluminum carrier rail</b>, 1000 x 18 x 7 mm 3'3" x 0.709 x 0.276 in</p>		<b>210-154</b>	1		<b>210-154</b>	1
 <p><b>Plastic end stop</b>, with WSB marking facility, for aluminum rail 210-154</p>	6 mm / 0.236 in wide grey	<b>209-122</b>	25	6 mm / 0.236 in wide grey	<b>209-122</b>	25
 <p><b>Mounting adapter</b>, for terminal blocks with snap-in mounting foot, for DIN 35 rail</p>	6 mm / 0.236 in wide grey	<b>209-120</b>	25	6 mm / 0.236 in wide grey	<b>209-120</b>	25
 <p><b>Mounting adapter with screw</b>, for terminal blocks with fixing flange, for DIN 35 rail</p>	6 mm / 0.236 in wide grey	<b>209-123</b>	25	6 mm / 0.236 in wide grey	<b>209-123</b>	25
 <p><b>Mounting adapter</b> for DIN 35 rail, can be used as <b>end stop</b></p>	6.5 mm / 0.256 in wide grey	<b>209-137</b>	25	6.5 mm / 0.256 in wide grey	<b>209-137</b>	25

\* For further approvals with corresponding ratings see pages 10.3 ff.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [wago manufacturer](#):*

Other Similar products are found below :

[750-460](#) [231-118/026-000](#) [231-303/026-000](#) [231-620/019-000](#) [257-403](#) [280-438](#) [280-831](#) [284-624](#) [210-111](#) [231-303/037-000](#) [231-446/001-000\\_NR](#) [232-216/026-000](#) [234-510](#) [264-726](#) [280-339](#) [0283-0671](#) [830-800/000-305](#) [750-512](#) [750-455](#) [51251782](#) [286-312](#) [713-1428/107-000](#) [731-138/048-000](#) [750-459](#) [750-517](#) [793-3505](#) [826-172](#) [859-304](#) [280-335](#) [231-535/001-000](#) [2604-1106](#) [2604-1504](#) [2606-1103/020-000](#) [2624-1103](#) [2626-3103/020-000](#) [821-104](#) [713-1107](#) [852-1411](#) [2106-1307](#) [2116-5307](#) [832-1205](#) [832-3604](#) [2009-110](#) [281-512/281-501](#) [286-336](#) [750-421](#) [750-838](#) [753-559](#) [750-1505](#) [787-732](#)