


Comfort series


5 mm embeddable



CE

Switching element function	NAMUR NC
Installation	embeddable
Rated operating distance s_n	5 mm
Assured operating distance s_a	0 ... 4.05 mm
Reduction factor r_{V2A}	0.74
Reduction factor r_{AI}	0.35
Reduction factor r_{Cu}	0.3
Nominal voltage U_o	8 V
Current consumption	
Measuring plate detected	≤ 1 mA
Measuring plate not detected	mA
Switching frequency f	0 ... 1000 Hz
Short circuit protection	yes
Polarity reversal protected	yes
Indication of the switching state	all direction LED, yellow
Ambient temperature	-25 ... 100 °C (248 ... 373 K)
EMC in accordance with	EN 60947-5-2; NE 21
Protection degree	IP67
Connection type	2 m, PVC-cable
Core cross-section	0.75 mm ²
Housing material	high grade steel
Sensing face	PBT
Standard conformity	DIN EN 60947-5-6 (NAMUR)
Effective internal capacity C_i C_i	≤ 90 nF ²⁾
Effective internal inductivity L_i L_i	≤ 100 μ H

Connection



06.11.2001

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Proximity Sensors](#) category:

Click to view products by [Pepperl & Fuchs](#) manufacturer:

Other Similar products are found below :

[01.001.5653.1](#) [70.340.1028.0](#) [70.360.2428.0](#) [70.364.4828.0](#) [70.810.1053.0](#) [72.360.1628.0](#) [73.363.6428.0](#) [9221350022](#) [980659-1](#) [QT-12](#)
[E2EX10D1NN](#) [E2E-X14MD1-G](#) [E2E-X2D1-G](#) [E2EX2ME2N](#) [E2E-X3D1-N](#) [10M](#) [E2E-X4MD1-G](#) [E2FMX1R5D12M](#) [E2K-F10MC1](#) [5M](#)
[EI1204TBOSL-6](#) [EI5515NPAP](#) [BSA-08-25-08](#) [IC08ANC15PO-K](#) [IMM2582C](#) [25.161.3253.0](#) [25.332.0653.1](#) [25.352.0653.0](#) [25.352.0753.0](#)
[25.523.3253.0](#) [9151710023](#) [922FS1.5C-A4P-Z774](#) [SC606ABV0S30](#) [SM952A126100LE](#) [A1220EUA-T](#) [F3S-A162-U](#) [CL18](#) [QT-08L](#)
[34.110.0010.0](#) [TL-C2MF1-M3-E4](#) [IA08BLF15NOM5](#) [IA08BSF15NOM5](#) [IA12ASF04DOM1](#) [IMM32188C](#) [IS2](#) [IS31SE5000-UTLS2-TR](#)
[34.110.0021.0](#) [34.110.0022.0](#) [CA150-120VACDC](#) [VM18VA3000Q](#) [XS508BSCBL2](#) [XS512BLNAM12](#)