

High Current Chokes

Special Features

- Very high current capacity
- Low DCR
- Epoxy coated ferrite bobbin core
- VW-1 rated shrink tubing to cover winding
- Self-leaded
- Fixed lead spacing
- Center hole for mechanical mounting
- Dielectric withstanding voltage:
2500 Vrms terminal to shrink tube cover;
1000 Vrms terminal to core
- Operating temperature -55 to +105 °C

Notes

* Rated current to cause 50 °C max. temperature rise and 5 % max. inductance drop

† RoHS Directive 2002/95/EC Jan 27 2003 including Annex.



Note: Major diameter of #6 screw = 0.138 "

Dimensions: Inches

1110 Series					
Part Number	L (μH) ±20 % @ 1 KHz	DCR Ω Max.	I, dc* (A)	Dim. C Approx.	Dim. D Nom.
1110-1R0M-RC	1.0	0.003	9	0.55	0.051
1110-1R2M-RC	1.2	0.003	9	0.55	0.051
1110-1R5M-RC	1.5	0.004	9	0.55	0.051
1110-1R8M-RC	1.8	0.004	9	0.55	0.051
1110-2R2M-RC	2.2	0.005	9	0.55	0.051
1110-2R7M-RC	2.7	0.005	9	0.55	0.051
1110-3R3M-RC	3.3	0.005	9	0.55	0.051
1110-3R9M-RC	3.9	0.006	9	0.55	0.051
1110-4R7M-RC	4.7	0.007	9	0.55	0.051
1110-5R6M-RC	5.6	0.007	9	0.55	0.051
1110-6R8M-RC	6.8	0.008	9	0.55	0.051
1110-8R2M-RC	8.2	0.009	9	0.55	0.051
± 10 %					
1110-100K-RC	10	0.010	9	0.55	0.051
1110-120K-RC	12	0.011	9	0.55	0.051
1110-150K-RC	15	0.015	7.2	0.53	0.045
1110-180K-RC	18	0.016	7.2	0.53	0.045
1110-220K-RC	22	0.020	5.5	0.53	0.045
1110-270K-RC	27	0.030	4.5	0.53	0.040
1110-330K-RC	33	0.040	4	0.53	0.040
1110-390K-RC	39	0.046	4	0.53	0.040
1110-470K-RC	47	0.062	2.8	0.53	0.036
1110-560K-RC	56	0.069	2.8	0.53	0.036
1110-680K-RC	68	0.077	2.8	0.50	0.032
1110-820K-RC	82	0.083	2.8	0.50	0.032
1110-101K-RC	100	0.095	2.8	0.50	0.032
1110-121K-RC	120	0.127	2	0.50	0.029
1110-151K-RC	150	0.181	1.6	0.50	0.029
1110-181K-RC	180	0.217	1.6	0.50	0.025
1110-221K-RC	220	0.240	1.6	0.50	0.025
1110-271K-RC	270	0.300	1.6	0.47	0.020
1110-331K-RC	330	0.336	1.3	0.47	0.020
1110-391K-RC	390	0.460	1	0.47	0.020
1110-471K-RC	470	0.636	0.8	0.47	0.020
1110-561K-RC	560	0.696	0.8	0.47	0.020

"-RC" suffix indicates RoHS compliance.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [bourns manufacturer](#):

Other Similar products are found below :

[PWR4412-2SDR0050F](#) [SRP1040-3R3M](#) [PWR4412-2SDR1000F](#) [SF-FP-LAB1](#) [SF-SP-LAB1](#) [PV36Z502C01B00](#) [3386F-FE1-202LF](#) [CMF-RLC50-10-0](#) [SM51295PEL](#) [PTF01-082T-103B2](#) [CMF-SD35A-2](#) [3547H-582-103A](#) [4118R-D48-103/104](#) [CMF-RD50-0](#) [4306H-BR4-000LF](#) [CRF0805-FX-R009ELF](#) [PT25012L](#) [1061-005](#) [5900-153-RC](#) [CRM2512-JW-222ELF](#) [6324](#) [6346](#) [6359](#) [CW201212-LAB1](#) [70F122AI-RC](#) [74F396AP-RC](#) [83A1D-B28-J10](#) [PCW1J-B24-KAB502](#) [PWR221T-30-1R00F](#) [PWR263S-20-20R0F](#) [H-1060](#) [1250-1S-480](#) [RJ26FW101](#) [RJR24FX104R](#) [2017-15-SMH-RPLF](#) [2200HT-821-V-RC](#) [RT22C2X502](#) [RT26C2X501](#) [91C1A-D24-A10L](#) [9230-76-RC](#) [SDE0805A-221K](#) [SDR0503-122JL](#) [SRP1238A-1R8M](#) [SRP1265A-R82M](#) [SRR0908-102YL](#) [SRU5028A-101Y](#) [SRU60-LAB1](#) [PEC11R-4225F-N0024](#) [PWR263S-20-27R0F](#) [3057L-1-102](#)