


Fuse holder terminal blocks for fuses 5x20 mm .197x.787 in. and 5x25 mm .197x.984 in.

Screw clamp  DIN 1 - DIN3

M 4/8.SF- 4 mm² blocks - 8 mm .315" spacing



M 4/8.SF


| Characteristics | | IEC NFC DIN | UL | CSA |
|------------------------------------|-----------------------|----------------------------|-----------|-----------|
| Wire size mm ² / AWG | Solid | 0.5 - 6 | 22-12 AWG | 22-12 AWG |
| | Stranded | 0.5 - 4 | | |
| Voltage | V | 630 (1)(2) | 600 (1) | 250 |
| Current | A | 6.3 | 10 | 10 |
| Rated wire size | mm ² / AWG | 4 mm ² | 12 AWG | 12 AWG |
| Wire stripping length | mm / inches | 9.5 mm / .37" | | |
| Recommended torque | Nm / lb.in | 0.5-0.8 Nm / 4.4-7.1 lb.in | | |

(1) Insulation voltage of terminal block - operating voltage : according to fuse.
(2) 400 V for block M 4/6.SFT

Selection

| Description | Type | Order P/N | Packaging | Weight kg |
|-----------------------------------|--------------------------------------|--------------------|-----------|--------------|
| Standard block grey | <input type="checkbox"/> M 4/8.SF | 1SNA 115 657 R2500 | 50 | |
| Block with test socket Ø2 mm grey | <input type="checkbox"/> M 4/8.SF | 1SNA 115 662 R2200 | 50 | |
| Standard block orange | <input type="checkbox"/> M 4/8.SF2 | 1SNA 105 135 R1100 | 50 | |
| Standard block beige V0 | <input type="checkbox"/> M 4/8.SF.V0 | 1SNA 195 657 R2600 | 50 | |

M 4/8.SFL - 4 mm² blocks - 8 mm .315" spacing




M 4/8.SFL

| Characteristics | | IEC NFC DIN | UL | CSA |
|------------------------------------|-----------------------|----------------------------|-----------|-----------|
| Wire size mm ² / AWG | Solid | 0.5 - 6 | 22-12 AWG | 22-12 AWG |
| | Stranded | 0.5 - 4 | | |
| Voltage | V | 400 | 600 | 250 |
| Current | A | 6.3 | 10 | 10 |
| Rated wire size | mm ² / AWG | 4 mm ² | 12 AWG | 12 AWG |
| Wire stripping length | mm / inches | 9.5 mm / .374" | | |
| Recommended torque | Nm / lb.in | 0.5-0.8 Nm / 4.4-7.7 lb.in | | |

Selection

| Description | Type | Order P/N | Packaging | Weight kg |
|---------------------------------------|------------------------------------|--------------------|-----------|--------------|
| Block with fusion indicator neon grey | <input type="checkbox"/> M 4/8.SFL | 1SNA 115 661 R2100 | 50 | |
| Block with fusion indicator 24V grey | <input type="checkbox"/> M 4/8.SFD | 1SNA 115 663 R2300 | 50 | |

M 4/8.SN - 4 mm² blocks - 8 mm .315" spacing



M 4/8.SN

| Characteristics | | IEC NFC DIN | UL | CSA |
|------------------------------------|-----------------------|----------------------------|-----------|-----------|
| Wire size mm ² / AWG | Solid | 0.5 - 6 | 22-12 AWG | 24-12 AWG |
| | Stranded | 0.5 - 4 | | |
| Voltage | V | 630 (1) | 600 | 250 |
| Current | A | 6.3 | 10 | 10 |
| Rated wire size | mm ² / AWG | 4 mm ² | 12 AWG | 12 AWG |
| Wire stripping length | mm / inches | 9.5 mm / .37" | | |
| Recommended torque | Nm / lb.in | 0.5-0.8 Nm / 4.4-7.1 lb.in | | |

(1) Insulation voltage of terminal block - operating voltage : according to fuse.

Selection

| Description | Type | Order P/N | Packaging | Weight kg |
|--|--------------------------------------|--------------------|-----------|--------------|
| Standard block grey body/blue grip | <input type="checkbox"/> M 4/8.SN | 1SNA 115 659 R0700 | 50 | |
| Standard block beige body/blue V0 grip | <input type="checkbox"/> M 4/8.SN.V0 | 1SNA 195 659 R0000 | 50 | |

Accessories

| | | | | | |
|-------------|--------|--------------------------------|--------------------|--------------------|----|
| End stop | BAM | 9.1 mm | 1SNA 103 002 R2600 | 50 | |
| End section | grey | <input type="checkbox"/> FEM8S | 1.5 mm | 1SNA 116 951 R1500 | 20 |
| | orange | <input type="checkbox"/> FEM8S | 1.5 mm | 1SNA 103 923 R1500 | 20 |



BAM



FEM8S

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [entrelec](#) manufacturer:

Other Similar products are found below :

[023000012](#) [023103024](#) [023000107](#) [1SNK505310R0000](#) [011762822](#) [016511417](#) [016340320](#) [1SNK516020R0000](#) [023300421](#)

[1SNK510010R0000](#) [018731214](#) [011870703](#) [010500220](#) [011511607](#) [023300227](#) [016049626](#) [017666704](#) [1SNK508411R0000](#) [023300320](#)

[023300001](#) [016548827](#) [012511813](#) [017301610](#) [011546820](#) [010500127](#)