
Item no.: 280-994
Product description: 4-conductor Ex e II through terminal block SUITABLE FOR EX
E APPLICATIONS



Produkt kann von Bild abweichen / product may differ

Packing unit 100 pieces

RoHS compliant

Product group	1 (Rail Mounted Terminal Blocks)
Cross section [mm ²]	0.2 - 2.5 mm ²
Cross section [AWG]	24 - 12 AWG
Connection method	CAGE CLAMP® CONNECTION
Measured voltage EN	550 V
Current intensity EN	20 A
Weight	9.156 g
Color	light gray
Wiring type	Front-entry
No. of connection Points	4
No. of potentials	1
Height	28 mm
Height	1.1 in
Width	5 mm
Width	0.197 in
Depth	75 mm
Depth	2.95 in
Strip length from	8 mm
Strip length to	9 mm

Strip length
Mounting

0.33 in
TS 35



Item no.	Admission office	Approval no.	Voltage [V]	Current [A]	Cross section [mm ²]
280-994	ABS	05-HG476175/3-PDA	800	24	2,5
280-994	AEX	E185892	550	20	28-12
280-994	BV	07436/Co	800	24	2,5
280-994	CCA	NL5855	800	24	2,5
280-994	CSA	154112-1536071	600	15	28-12
280-994	DNV	E-10423	800	24	2,5
280-994	GL	17295-00HH	800	24	2,5
280-994	GOSENERGO-Ex	99.041	550	20	2,5
280-994	KEMA	2082859.07	800	24	2,5
280-994	LR	91/20112(E6)	800	24	2,5
280-994	PRS	TE/1718/880590/08	800	24	2,5
280-994	PTB	PTB99AteX3109U	550	20	2,5
280-994	RMR	11130002	800	24	2,5
280-994	RosTest	8189158	550	20	2,5
280-994	UR	E45172	600	20	28-12

Sorting criteria: admission office - approval number

© WAGO Kontakttechnik GmbH & Co. KG

Specifications are subject to changes and errors may be expected

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [wago manufacturer](#):

Other Similar products are found below :

[750-460](#) [231-118/026-000](#) [231-303/026-000](#) [231-620/019-000](#) [257-403](#) [280-438](#) [280-831](#) [284-624](#) [210-111](#) [231-303/037-000](#) [231-446/001-000_NR](#) [232-216/026-000](#) [234-510](#) [264-726](#) [280-339](#) [0283-0671](#) [830-800/000-305](#) [750-512](#) [750-455](#) [51251782](#) [286-312](#) [713-1428/107-000](#) [731-138/048-000](#) [750-459](#) [750-517](#) [793-3505](#) [826-172](#) [859-304](#) [280-335](#) [231-535/001-000](#) [2604-1106](#) [2604-1504](#) [2606-1103/020-000](#) [2624-1103](#) [2626-3103/020-000](#) [821-104](#) [713-1107](#) [852-1411](#) [2106-1307](#) [2116-5307](#) [832-1205](#) [832-3604](#) [2009-110](#) [281-512/281-501](#) [286-336](#) [750-421](#) [750-838](#) [753-559](#) [750-1505](#) [787-732](#)