

# USB 2.0 Lead


## USB A Male to USB B Male

pro-SIGNAL






### Specifications:

Cable Wiring	: 7/0.1CU×1P+7/0.15CU×2C+ADB (48/0.12ALMG)
Cable Printing	: USB 2.0 Cable Fully rated 80°C 30V
<b>Connector A</b>	: USB 2.0 A Male Solder Type
Insulation	: White
Contact	: Brass, Gold Plated
Shell	: Fe, Nickel Plated
<b>Connector B</b>	: USB 2.0 B Male Solder Type
Insulation	: White
Contact	: Brass, Gold Plated
Shell	: Fe, Nickel Plated
Over Mold	: PVC
Parameter Settings	: CT-8681FA
Conductive Resistance	: 1 to 5Ω
Insulative Resistance	: 5MΩ (Min.)
Hi-Pot	: 250V/AC DC, 1.5mA/I, 50Hz, 0.03s



Dimensions : Millimetres



# USB 2.0 Lead

## USB A Male to USB B Male

pro-SIGNAL

### Part Number Table

Description	Colour	Lead Length (m)	Part Number
USB Cable Assembly, USB A / B	Red	2	PSG90042
	Clear		PSG90030
	Blue Transparent		PSG90039
	Transparent		PSG90033
	White		PSG90044

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. pro-SIGNAL is the registered trademark of the Group. © Premier Farnell plc 2012.

[www.element14.com](http://www.element14.com)  
[www.farnell.com](http://www.farnell.com)  
[www.newark.com](http://www.newark.com)  
[www.cpc.co.uk](http://www.cpc.co.uk)

pro-SIGNAL

# X-ON Electronics

Authorized Distributor

*Click to view similar products for [Pro Signal](#) manufacturer.*

Other Similar products are found below :

[JR803025M](#) [SPC23168](#) [PSG01325](#) [PSG90957](#) [PSG90815](#) [PSG01569](#) [PS11208](#) [PS11185](#)

[PS11360](#) [PS11060](#) [PSG90809](#) [PSG90813](#) [PSG04068](#) [PSG00282](#) [FV023HLBNY303](#)

[PSG01336](#) [PSG90961](#) [PSG90812](#) [PSG01501](#) [PS11386](#) [PS11160](#) [PS11161](#) [PS11165](#)

[PS11306](#) [PS11095](#)