

## Neon Indicators

### (Neon, LED and Filament Lamps) - Page 2 of 5



#### Colours and voltages

|                      |  |
|----------------------|--|
| <b>Neon</b>          | Red, Amber, Green, Clear.<br>100/130V (marked 110V), 200/250V  |
| <b>LED</b>           | (marked 230V)  |
| <b>Filament lamp</b> | Red, Yellow, Green<br>2.0/2.2V. Resistors for other voltages available.<br>Red, Amber, Green, Clear and Blue.<br>6V, 12/14V, 24/28V. |

#### To create a catalogue no.:

Refer to the 2 columns below (terminal & type).



























Then state:

Lens colour, voltage and whether neon, LED or filament lamp.

[\\*Additional Information / Temperature Rating Details](#)

[UL file E63363](#) [CSA file LR29381](#)

| TERMINALS |     | TYPE           | DIMENSIONS   |                      |
|-----------|-----|----------------|--|----------------------|
| L         |     | L 2951 00<br>  | <br>8.0mm<br><br>0.8-1.6mm max.<br><br>T85 °C            | Chrome bezel<br><br> |
| L         |     | (C)0273 00<br> | <br>9.0mm<br><br>2.0mm max.<br><br>T85°C<br><br>*T125°C  | <br>                 |
| K         | 2.8 |                |  |                      |
| H         | 4.8 |                |  |                      |
| C         | 6.3 |                |  |                      |
| L         |     | (C)0278 00<br> | <br>9.0mm<br><br>2.0mm max.<br><br>T85°C<br><br>*T125°C  | <br>                 |
| K         | 2.8 |                |  |                      |
| H         | 4.8 |                |  |                      |
| C         | 6.3 |                |  |                      |
| L         |     | (C)0276 AA<br> | <br>9.5mm<br><br>0.8 - 2.4mm<br><br>T85°C<br><br>*T125°C | <br>                 |
| K         | 2.8 |                |  |                      |
| H         | 4.8 |                |  |                      |
| C         | 6.3 |                |  |                      |

|   |   |  |  |  |
|---|---|--|--|--|
| <p>L </p>      | <p>(C)0275 00</p>   | <p> 10.0mm</p>             |   |  <p>Ø13.3</p> |
| <p>K  2.8</p> |  | <p> 12.0mm max.</p>       |  |  |
| <p>H  4.8</p> |   | <p> T85°C<br/>*T125°C</p> |  |  |
| <p>C  6.3</p> |  |  |  |  |
| <p>L </p>     | <p>(C)0275 00 with chrome bezel</p>   | <p> 10.0mm</p>            |  |  <p>Ø15.6</p> |
| <p>K  2.8</p> |  | <p> 12.0mm max.</p>       |  |  |
| <p>H  4.8</p> |   | <p> T85°C<br/>*T125°C</p> |  |  |
| <p>C  6.3</p> |  |  |  |  |

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [arcolectric manufacturer](#):*

Other Similar products are found below :

[H8500XBBBG076G](#) [NL275C3A-CHROME](#) [NL67H2A](#) [C1510AABW](#) [C1550WABWCL050B](#) [C5503PLBR5](#) [279672](#) [H8500XBDDR076R](#)  
[C1550WABB602AW](#) [3700](#) [LE2870C5G](#) [LHM62R](#) [512F10AE222](#) [64F500FA383](#) [C1350XBMBBG](#) [C1300AAAAA](#) [C1500XAMBBR](#)  
[T0340RA](#) [L104100FAF](#) [H8503VBBR2](#) [H8503VBNAE](#) [NL67C2R](#) [H8660VBBB](#) [C3900BA](#) [NL2950BWL2A](#) [T22208EAAG](#)  
[C6053ALBG31197WB](#) [NL177WL2R](#) [C480AABA7](#) [H8503VBBR2-B](#) [468](#) [LH1050WL-3602](#) [T0063AOFAD](#) [C1560AAAAA](#)  
[NL2870WL3R-VDE](#) [NL177WL3G](#) [C5503ATBR2](#) [C6090ALBR2-1197W-B](#) [LE177C39007](#) [LE276C39018](#) [LE2951WL5G](#) [A104700BLACK](#)  
[H1570ABBB-730W](#) [3852510KBL](#) [LH692G](#) [C1353VQ0/1GRN](#) [C1250ANTAA](#) [MP0045/1D0NN000S](#) [K1911VA](#) [1892](#)