

SOT23 N-CHANNEL ENHANCEMENT MODE VERTICAL DMOS FET


VN10LF

ISSUE 2 – JANUARY 1996

FEATURES

- * 60 Volt V_{DS}
- * $R_{DS(on)}=5\Omega$

PARTMARKING DETAIL – MY



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Drain-Source Voltage	V_{DS}	60	V
Continuous Drain Current at $T_{amb} = 25^{\circ}C$	I_D	150	mA
Pulsed Drain Current	I_{DM}	3	A
Gate Source Voltage	V_{GS}	± 20	V
Power Dissipation at $T_{amb} = 25^{\circ}C$	P_{tot}	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Drain-Source Breakdown Voltage	BV_{DSS}	60			V	$I_D=100\mu A, V_{GS}=0V$
Gate-Source Breakdown Voltage	$V_{GS(th)}$	0.8		2.5	V	$I_D=1mA, V_{DS}=V_{GS}$
Gate Body Leakage	I_{GSS}			100	nA	$V_{GS}=\pm 20V, V_{DS}=0V$
Zero Gate Voltage Drain Current (1)	I_{DSS}			10	μA	$V_{DS}=60V, V_{GS}=0V$
On State Drain Current(1)	$I_{D(on)}$	750			mA	$V_{DS}=15V, V_{GS}=10V$
Static Drain Source On State Resistance (1)	$R_{DS(on)}$			5.0 7.5	Ω	$V_{GS}=10V, I_D=500mA$ $V_{GS}=5V, I_D=200mA$
Forward Transconductance (1)(2)	g_{fs}	100			mS	$V_{DS}=15V, I_D=500mA$
Input Capacitance (2)	C_{iss}			60	pF	$V_{DS}=25V, V_{GS}=0V$ $f=1MHz$
Common Source Output Capacitance (2)	C_{oss}			25	pF	
Reverse Transfer Capacitance (2)	C_{rss}			5	pF	
Turn-On Time (2)(3)	$t_{(on)}$		3	10	ns	$V_{DD}\approx 15V, I_D=600mA$
Turn-Off Time (2)(3)	$t_{(off)}$		4	10	ns	

(1) Measured under pulsed conditions. Width=300 μs . Duty cycle $\leq 2\%$ (2) Sample test.

(3) Switching times measured with 50 Ω source impedance and <5ns rise time on a pulse generator

Spice parameter data is available upon request for this device

For typical characteristics graphs see ZVN3306F datasheet.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [diodes](#) incorporated [manufacturer](#):

Other Similar products are found below :

[1.5KE62A-T](#) [MMSZ5232BQ-13-F](#) [DMN2065UW-7](#) [AH3782-SA-7](#) [AP7365-39WG-7](#) [6A10-T](#) [MBRB10100CT](#) [AZ1117EH-5.0TRG1](#)
[AZV3002S-13](#) [PAM2863EV1](#) [SBRT25U60SLP-13](#) [LM2904AQM8-13](#) [GBPC1506](#) [GBU804](#) [GBU808](#) [BCR401UW6-7](#) [DMP4013LFG-7](#)
[DMTH6009LK3Q-13](#) [SB560-T](#) [AP3125AKTR-G1](#) [FMMT491ATA](#) [AZV832MMTR-G1](#) [6A6-T](#) [BZX84C5V1TS-7-F](#) [DMP6180SK3-13](#)
[BZT52C15LP-7](#) [74LVC1G58W6-7](#) [DDTC114ELP-7](#) [BAS40](#) [1N5402-T](#) [ZMR330FTA](#) [ZVN4525E6TA](#) [SBR40100CT](#) [FZT605TA](#)
[BZT52C2V4Q-7-F](#) [BZX84C15-13-F](#) [BZX84C3V9Q-7-F](#) [BZX84C4V7-13-F](#) [BZX84C5V1-13-F](#) [BZX84C3V9](#) [ZXLD1370/1EV4](#)
[AP64501SP-EVM](#) [AP63203WU-EVM](#) [AP63200WU-EVM](#) [AP63201WU-EVM](#) [AP63356DV-EVM](#) [DMN30H4D0L-7](#) [DFLT48A-7](#)
[ZVNL110A](#) [ZXSC100N8TA](#)