

Where To Buy

Enter Zip Code:

Enter Quantity:

GO

Sta-Kon®

PRINT

Ring Terminal

T&B Catalog Number: RZ22-2
UPC Number: 78621080452
Status: Active

Description:
 Insulated Nylon Ring Terminal For Wire Range 26-22 Stud Size #2, Yellow

ROHS SUBMITTAL PACKAGE

Features

- Self-insulated with high dielectric-strength nylon sleeves. An inner bronze insula the flexing radius of the conductor and eliminates conductor creep.

General

Insulation Type	Insulated Nylon
Terminal Series	RZ
Material	Copper
Finish	Electro -Tin Plated
Color	Yellow
Wire Range	26-22
Stud Size	#2

Dimension Information

Maximum Insulation (inches)	.083
Stock Thickness	.02
A (inches)	.57
B (inches)	.14
C (inches)	.13
M (inches)	.49

Specifications

Temperature Rating	105°C
Voltage Rating	600V
Flammability Rating	UL 94 V-2

Tooling


 Tool Charts [Click Here](#)

Application Tools [WT1452](#)
 Recommended Tool [ERG4006](#)

Packaging

Order Multiple	100
Inner Package	100
Outer Package	500
Package Type	Standard
Package Height	2.6
Package Length	4.8
Package Width	1.8
T&B Sold in UOM	Each
T&B Weight Per UOM	0.15 lbs. per 100

Application Support

 T&B Sales Drawings [wsd-000204](#)

 Overview [Click Here](#)

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [abb](#) manufacturer:

Other Similar products are found below :

[TV10-516R](#) [017667013](#) [RF727](#) [2CMA100178R1000](#) [2CMA100163R1000](#) [5SDD 92Z0401](#) [ESV14-BS](#) [EZS-21-250](#) [F204AC-40/0.03](#) [F362-25/0.03](#) [GJL1211201R8000](#) [GJL1211501R8000](#) [GJL1213001R0017](#) [GJL1213001R0101](#) [GJL1311001R0011](#) [GJL1311001R0101](#) [GJL1311001R8010](#) [GJL1311201R0001](#) [GJL1313001R0011](#) [GJL1313001R0101](#) [GJL1317201R0001](#) [A40-30-10-84](#) [AF09-30-01-11](#) [AF460-30-11-68](#) [1455](#) [B14-250](#) [EF45-30](#) [ERG297](#) [HSC2-20](#) [1SAM201904R1001](#) [1SAM350000R1003](#) [1SAZ721201R1009](#) [1SAZ721201R1014](#) [1SAZ721201R1025](#) [1SBL157001R1310](#) [1SBL277001R1300](#) [1SBL277001R4100](#) [1SBL367001R1300](#) [1SBL387001R4100](#) [1SBN010110R1001](#) [1SBN010110R1010](#) [1SBN010140R1022](#) [1SBN010140R1122](#) [1SDA057197R1](#) [1SFA611101R1002](#) [1SFA611130R1103](#) [1SFA611131R1101](#) [1SFA611143R1101](#) [1SFA611202R1108](#) [1SFA611203R1108](#)