

LOGO! TD TEXTDISPLAY,  
FOR LOGO! FROM ..0BA6, 4 LINES,  
WITH CABLE (2.5M) AND MOUNTING ACCESSORIES,  
CONFIGURATION WITH LOGO! SOFT COMFORT V6.0



General information	
Application area	Connection to all LOGO! basic units from ..0BA6
Delivery quantity in pieces	1
Operator control and monitoring	
Illuminant	LED
Operating / fault messages	
Number of lines	4
Number of characters per line	24
Display	
Design of display	STN
graphics-enabled	No
Control elements	
Keyboard fonts	
Keys with LED	No
Number of configurable system keys	15
System keys	Yes
Numeric/alphabetical input	
Numeric keyboard	No
Alphanumeric keyboard	No

Supply voltage	
Type of supply voltage	DC
permissible range, lower limit (DC)	20.4 V
permissible range, upper limit (DC)	28.8 V
Interfaces	
Number of RS 232 interfaces	1
Number of other interfaces	1
Industrial Ethernet	
Number of industrial Ethernet interfaces	0
Degree and class of protection	
IP40	Yes
Ambient conditions	
Operating temperature	
Min.	0 °C
max.	55 °C
Accessories	
Function description	Connecting cable length 2.5 m
belongs to product	LOGO!
Dimensions	
Width	128.2 mm
Height	86 mm
Depth	38.7 mm
Dimensions and weight	Length 2.5 m
Weight	
Weight, approx.	220 g
Status	Apr 20, 2013

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [siemens](#) manufacturer:*

Other Similar products are found below :

[5SJ4101-7HG40](#) [5SL6225-7](#) [5ST2144](#) [5ST2167](#) [5SX2125-7](#) [5SX2132-7](#) [5SX2320-7](#) [5SX2340-7](#) [5SX9200](#) [5SY4106-8](#) [5SY6220-7](#)  
[6EP1321-5BA00](#) [6EP3333-8SB00-0AY0](#) [6ES5451-7LA11](#) [6ES7322-1BF01-0AA0](#) [D11CEU1](#) [PD63F160](#) [FXD63B175](#) [8WA1011-2SF25](#)  
[8WA1721](#) [8WA1815](#) [8WA8848-0AC](#) [8WA8-848-0AM](#) [8WA8-848-0AN](#) [8WA8-848-0AT](#) [8WA8-848-0AX](#) [8WA8-848-0BD](#) [8WA8-848-](#)  
[0BF](#) [8WA8-848-0BL](#) [8WA8-848-0BP](#) [8WA8-848-0BQ](#) [14DP32AC81](#) [ED21B100](#) [B32523-.47@400V-J](#) [B65541-T25-A48](#) [B65549-E4-X23](#)  
[B65812-B1512-T1](#) [B66317-G0000-X127](#) [B66337-G0500-X127](#) [B66417-G-X167](#) [B82724-J](#) [8WA1201](#) [8WA1854](#) [8WA1870](#) [8WA8-848-](#)  
[0AK](#) [8WA8-848-0AV](#) [8WA8-848-0BC](#) [8WA8-848-0BG](#) [8WA8-848-0BJ](#) [8WA8-848-0BK](#)