

Waterproof Type Voltage Tester



Description

This tester has been designed in accordance with the latest international safety standards. The combivolt tester is a fully automatic voltage indicator capable of measuring AC/DC voltage up to 690V. This unit has visual and acoustic continuity indication

Features

- Water-Proof (IP65)
- Auto Range
- Work Light
- Low Battery Indication : Short circuit two leads,LED and beeper off when the battery is low
- LCD AC/DC Voltage Display : 24V to 690V

Specifications

	Range	
LED AC/DC Voltage Indication (V)	12V	0 to 10V
	24V	17V \pm 2V
	50V	35V \pm 6V
	120V	80V \pm 20V
	230V	165V \pm 20V
	400V	300V \pm 30V
	690V	510V \pm 40V
Phase Rotation Test	Operating Voltage : 0V to 690V	
	Frequency : 50Hz to 60Hz	
Single Lead(L2)Voltage Detection	Operating Voltage : 100V to 690V	
	Frequency : 50Hz to 400Hz	
Continuity Test	Resistance : 0 to 400k Ω	
	Beeper and LED light Indicator	
Polarity Detection	Positive & Negative	

General Characteristic

Power	1.5V Cell (R03) \times 2
Product Colour	Orange and Grey
Product Net Weight	210g
Product Size	275mm \times 51mm \times 30mm
Standard Accessories	1.5V Cell
Safety Rating	CAT IV 600V

Part Number Table

Description	Part Number
Voltage Tester, 0 to 690V	72-9395

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.



X-ON Electronics

Authorized Distributor

Click to view similar products for [Greenlee](#) category.

Click to view products by [Tenma](#) manufacturer.

Other Similar products are found below :

[PA9655](#) [PA2530](#) [PA901014](#) [01801](#) [PA2240](#) [PA3242](#) [PA1250](#) [PA1356](#) [PA1340](#) [PA2245](#)
[VOLTSTICKPRO12VAC](#) [PA1328](#) [PA901053](#) [PA8010](#) [PA2097](#) [7304](#) [AT8LK](#) [PA8036](#)
[PA2243](#) [PA8049](#) [247215](#) [35651](#) [PA9614](#) [PA8021](#) [TS25D](#)