



Connectors for mains connection

CA-series



Product description









Robust, universal circular connector for machinery engineering in general, control engineering, electrical medical equipment as well as for the chemical industry.

- International approvals for worldwide use: VDE, UR, SEV, CSA

- Housings made of impact-resistant plastic with screw locking system for troublefree, permanent connections
- Easy handling for a quick assembly with integrated strain relief
- Useful in industry due to protection against dust and water

Basic data

Operating voltage: 250 V AC / DC, (400 V AC 3-pole)
 Operating current: 10 A AC / DC (at 20° C), 16 A AC 3-pole (at 20° C)
 Protection class: IP 67
 Pollution severity class: 3
 Strain relief by means of cable: 6 mm-12 mm
 Contact surface: Cu Zn

Type		Number of poles	Description	Order no.
 CA 3 LS		3 + PE	Cable connector Type of connection: screw Conductor cross-section: max. 1.5 mm ² Operating voltage: 250 V DC / 400 V AC Operating current: 10 A DC / 16 A AC	934 124-100
 CA 3 LD		3 + PE	Cable socket Type of connection: screw Conductor cross-section: max. 1.5 mm ² Operating voltage: 250 V DC / 400 V AC Operating current: 10 A DC / 16 A AC	934 125-100
 CA 3 W LS		3 + PE	Cable connector Type of connection: screw Conductor cross-section: max. 1.5 mm ² Operating voltage: 250 V DC / 400 V AC Operating current: 10 A DC / 16 A AC	934 128-100
 CA 3 W LD		3 + PE	Cable socket Type of connection: screw Conductor cross-section: max. 1.5 mm ² Operating voltage: 250 V DC / 400 V AC Operating current: 10 A DC / 16 A AC	934 129-100

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [hirschmann](#) manufacturer:

Other Similar products are found below :

[931298001 GSP 211 PG11](#) [934828001 BRSCIS 4D/9](#) [930011200 MAB 6](#) [932326100 CA 6 GS](#) [G 30 KW 3 M](#) [831530400 CA 00 SD 1](#)
[934077105](#) [934066788](#) [934061103](#) [934059104](#) [930046100](#) [975090703](#) [943301-001](#) [934061704](#) [STAK2](#) [PRUEF1SW](#) [SPIDER-PL-20-](#)
[05T1999999TZ9HHHH](#) [BAT867-RUSW99AU999AT199L999ZHX](#) [930136106](#) [930317804](#) [934066105](#) [934076103](#) [934086104](#) [934086188](#)
[973929000](#) [934157101](#) [934077106](#) [934064104](#) [932794001](#) [973601101](#) [GECKO 4TX](#) [972309101](#) [934100707](#) [975455709](#) [975455701](#)
[973528101](#) [931297006](#) [MESAP 43650](#) [932140100](#) [STAK 3 N SCHWARZ](#) [932507005](#) [XZC 0704](#) [975694707](#) [MLSWG100/2.5RT](#) [BAT867-](#)
[RUSW99CU999AT199L999ZHX](#) [934081100](#) [934089101](#) [934090100](#) [973929001](#) [975017701](#) [975106101](#) [934157100](#)