

Female Crimp

- ❖ Part numbers are for housings and the equivalent number of contacts.
- ❖ Contacts are rear insertable.
- ❖ For British Standard versions see pages 18 to 19.
- ❖ Mates with male connectors on pages 27 to 33.
- ❖ Spare contacts are available – see page 25.



SINGLE ROW	CALCULATION	DOUBLE ROW	CALCULATION
	A B + 5.15		A B + 5.15
	B (Total no. of contacts - 1) x 2		B Total no. of contacts - 2

TOOLS	WIRE STRIPPING DETAILS
<p>Recommended Crimp Tool – M22520/2-01 Positioner – T5747 Contact Insertion/Removal Tool – Z80-280</p> <p>See pages 87 to 89</p> <p>❖ Instruction sheets available at www.harwin.com/downloads/instructions</p>	

HOW TO ORDER

M80 - XXX XX XX

SERIES CODE

TYPE

SINGLE	DOUBLE	
798	788	Extra Small Bore (28-32 AWG), Hi-Temp Plastic
845	844	Small Bore (24-28 AWG), Hi-Temp Plastic
611	613	Large Bore (22 AWG), Hi-Temp Plastic
898	888	Small Bore (24-28 AWG)
899	889	Large Bore (22 AWG)

FINISH

01	Gold + Tin (M80-788/789/888/889/898/899)	PG
05	Gold (M80-788/789/888/889/898/899)	PG
42	Gold + Tin (M80-611/613/844/845)	PG
45	Gold (M80-611/613/844/845)	PG

TOTAL NO. OF CONTACTS

02 to 07, 17	Single Row
04, 06, 08, 10, 12, 14, 16, 18, 20, 26, 34	Double Row

All dimensions in mm.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [Harwin](#) manufacturer:

Other Similar products are found below :

[95000-104TRLF](#) [10135584-644402LF](#) [DF62W-EP2022PCA](#) [95000-106TRLF](#) [DF62W-2022SCA](#) [DF62W-EP2022PC](#) [2203348](#) [DF62W-2022SC](#) [1084018](#) [1029039](#) [1084017](#) [802-10-012-10-002000](#) [1112640](#) [1112639](#) [000-34000](#) [0009482033](#) [0009507031](#) [57102-S06-03LF](#) [57202-S52-04LF](#) [PCN6-15S-2.5E](#) [0039019024](#) [58102-G61-06LF](#) [582553-1](#) [0009485154](#) [0009508121](#) [0022285053](#) [0050291907](#) [018731A](#) [LY20-4P-DT1-P1E-BR](#) [02.125.8002.8](#) [60101931](#) [60598-1 \(Cut Strip\)](#) [M1625-3R/100](#) [61062-3](#) [61082-181009](#) [636-1427](#) [638009-1](#) [641938-9](#) [641991-4](#) [644168-1](#) [647662-1](#) [65039-019ELF](#) [65817-002LF](#) [65817-015LF](#) [65863-015LF](#) [66207-023LF](#) [67016-026LF](#) [67046-001LF](#) [67095-007LF](#) [67230-005LF](#)