

CO15 Carbon Monoxide (CO) Meter



Check CO levels up to 999ppm with the push of a button using Model CO15. An audible alarm indicator will continuously beep starting at 25ppm (preset warning level - value can be adjusted) and the display will flash until the CO level goes down to normal range. A backlight on the display can be used for low light areas. The meter comes complete with batteries, wrist strap, and pouch.

Applications:

- Ambient air safety checks on residential appliances
- HVAC service on furnaces and hot water heaters
- Home inspections
- Industrial environments where the accumulation of CO is possible

Features

- Dual LCD simultaneously displays Carbon Monoxide (CO) level and maximum CO reading taken from when the meter was powered on
- Long life electrochemical sensor
- Adjustable CO warning level at 25, 30, 35, 45, 50, 70, 100 and 200ppm (alarm is preset to 25ppm)
- Audible alarm when CO level reaches the warning set point level
- Choose from 3 calibration points: 0 (preset), 100, and 500ppm
- Backlit display feature for easy viewing in dimly lit areas
- Auto power off after 15 minutes
- Low battery indicator
- Complete with 3 AAA batteries, wrist strap and pouch

Specifications	Range	Resolution	Basic Accuracy
Carbon Monoxide (CO)	0 to 999ppm	1ppm	±20% @ 0 to 100ppm; ±15% @ 100 to 500ppm
Dimensions	6.9x1.9x1.1" (175x47x28mm)		
Weight	5.6oz (158.8g)		

Ordering

CO15 Carbon Monoxide (CO) Meter



UPC Code: 793950500156

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Environmental Test Equipment](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[CW40](#) [F150C10E3DRT](#) [F150LTC20](#) [F150CD10E2](#) [F150L75](#) [F150LRS](#) [S-11](#) [FLUKE-LDG](#) [382153](#) [FM100](#) [RH210](#) [382253](#) [MO290-P](#)
[GEO-CABLE-REEL-50M](#) [T197914](#) [RD300-L](#) [IR11BD](#) [IR11GM](#) [IR12GM](#) [IR21BD](#) [IR31CE](#) [IR32BC](#) [IR33BC](#) [MP7217TC](#) [NGM-1](#) [SGX-](#)
[7NH3](#) [UT381](#) [F150-SLC50](#) [AW-CO-1000](#) [AW-NmHc-100](#) [3.000.401](#) [AX-7535](#) [CS-9S6SS-A](#) [P 2800 A](#) [P 2801](#) [P 2802](#) [P 5039](#) [P 5130](#) [P](#)
[5055](#) [P 5060](#) [P 5065](#) [P 5086](#) [P 5090](#) [P 5110](#) [P 5115](#) [P 5135](#) [P 5140](#) [P 5145](#) [P 5150](#) [P 5160](#)