

Junction FETs* (Continued)

Switches / Choppers N-Channel



TO-18



TO-92

CASE	TYPE NO.	$r_{DS(on)}$	V_{GS} (off)		I_{DSS}		$V_{(BR)GSS}$	C_{iss}	C_{rss}	t_{on}	t_{off}	PIN OUT
		(Ohm)	(V)		(mA)		(V)	(pF)	(pF)	(ns)	(ns)	
		MAX	MIN	MAX	MIN	MAX	MIN	MAX	MAX	MAX	MAX	
TO-18	2N3970	30	4.0	10	50	150	40	25	6.0	20	30	SDG
TO-18	2N3971	60	2.0	5.0	25	75	40	25	6.0	30	60	SDG
TO-18	2N3972	100	0.5	3.0	5.0	30	40	25	6.0	80	100	SDG
TO-18	2N4091	30	5.0	10	30	--	40	16	5.0	25	40	SDG
TO-18	2N4092	50	2.0	7.0	15	--	40	16	5.0	35	60	SDG
TO-18	2N4093	80	1.0	5.0	8.0	--	40	16	5.0	60	80	SDG
TO-18	2N4391	30	4.0	10	50	150	40	14	3.5	15	20	SDG
TO-18	2N4392	60	2.0	5.0	25	75	40	14	3.5	15	35	SDG
TO-18	2N4393	100	0.5	3.0	5.0	30	40	14	3.5	15	50	SDG
TO-18	2N4856	25	4.0	10	50	--	40	18	8.0	9.0	25	SDG
TO-18	2N4856A	25	4.0	10	50	--	40	10	4.0	8.0	20	SDG
TO-18	2N4857	40	2.0	6.0	20	100	40	18	8.0	10	50	SDG
TO-18	2N4857A	40	2.0	6.0	20	100	40	10	3.5	10	40	SDG
TO-18	2N4858	60	0.8	4.0	8.0	80	40	18	8.0	20	100	SDG
TO-18	2N4858A	60	0.8	4.0	8.0	80	40	10	3.5	16	80	SDG
TO-18	2N4859	25	4.0	10	50	--	30	18	8.0	9.0	25	SDG
TO-18	2N4859A	25	4.0	10	50	--	30	10	4.0	8.0	20	SDG
TO-18	2N4860	40	2.0	6.0	20	100	30	18	8.0	10	50	SDG
TO-18	2N4860A	40	2.0	6.0	20	100	30	10	3.5	10	40	SDG
TO-18	2N4861	60	0.8	4.0	8.0	80	30	18	8.0	20	100	SDG
TO-18	2N4861A	60	0.8	4.0	8.0	80	30	10	3.5	16	80	SDG
TO-92	2N5555	150	--	--	15	--	25	5.0	1.2	10	25	DSG
TO-92	PN4091	30	5.0	10	30	--	40	16	5.0	25	40	DSG
TO-92	PN4092	50	2.0	7.0	15	--	40	16	5.0	35	60	DSG
TO-92	PN4093	80	1.0	5.0	8.0	--	40	16	5.0	60	80	DSG
TO-92	PN4391	30	4.0	10	50	150	40	14	3.5	15	20	DSG
TO-92	PN4392	60	2.0	5.0	25	75	40	14	3.5	15	35	DSG
TO-92	PN4393	100	0.5	3.0	5.0	30	40	14	3.5	15	55	DSG

P-Channel

TO-18	2N5114	75	5.0	10	30	90	30	25	7.0	16	21	SGD
TO-18	2N5115	100	3.0	6.0	15	60	30	25	7.0	30	38	SGD
TO-18	2N5116	150	1.0	4.0	5.0	25	30	25	7.0	50	80	SGD

*Some JFET types available on special order only; please consult factory

(25-June 2012)

Central[™]
Semiconductor Corp.
www.centalsemi.com



OUTSTANDING SUPPORT AND SUPERIOR SERVICES

PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix "TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix "PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for JFET category:

Click to view products by [Central Semiconductor](#) manufacturer:

Other Similar products are found below :

[MCH3914-8-TL-H](#) [F5606](#) [2SK536-TB-E](#) [SMMBF4393LT1G](#) [CPH3910-TL-E](#) [CPH5901F-TL-E](#) [CPH5901G-TL-E](#) [CPH5902H-TL-E](#)
[424147G](#) [TF202THC-4-TL-H](#) [MCH3914-7-TL-H](#) [MCH5908H-TL-E](#) [DSK5J01R0L](#) [CPH5902G-TL-E](#) [CPH5905G-TL-E](#) [CPH5905H-TL-E](#)
[2SK304E-SPA](#) [2SK545-11D-TB-E](#) [2SK771-5-TB-E](#) [2SK2539-7-TB-E](#) [2SK932-22-TB-E](#) [2SK2394-7-TB-E](#) [NSVJ2394SA3T1G](#)
[MMBFJ175LT3G](#) [SMPJ270TR](#) [2SK208-GR\(TE85L\)](#) [MMBF4416](#) [MMBF5103](#) [MMBF5484](#) [MMBFJ175](#) [MMBFJ176](#) [MMBFJ270](#)
[MMBF4393](#) [NPT1004D](#) [2SK1069-5-TL-E](#) [2SA1781-6-TB-E](#) [NSVJ3910SB3T1G](#) [2N5116](#) [2N5116](#) [CMPF4392 TR](#) [2N4092](#) [2N4093](#)
[CMPP6028 TR](#) [2N4117](#) [2N3958](#) [SNJ450113](#) [IFN3993](#) [IFN5911](#) [IFN406](#) [2N4393](#)