

CentralTM Semiconductor Corp.

145 Adams Avenue, Hauppauge, NY 11788 USA
Tel: (631) 435-1110 • Fax: (631) 435-1824

Manufacturers of World Class Discrete Semiconductors

2N6306
2N6307
2N6308

NPN Silicon Transistor

JEDEC TO-3 Case

DESCRIPTION

The CENTRAL SEMICONDUCTOR 2N6306, 2N6307, and 2N6308 are NPN Silicon Power Transistors designed for high voltage inverters, switching regulators, line operated amplifiers, and switching power supplies.

MAXIMUM RATINGS (T=25°C)

		2N6306	2N6307	2N6308
Collector-Emitter Voltage	V _{CEO}	250V	300V	350V
Collector-Base Voltage	V _{CB0}	500V	600V	700V
Emitter-Base Voltage	V _{EB0}		8V	
Collector Current	I _C		8A	
Base Current	I _B		4A	
Power Dissipation	P _T		125W	
Operating & Storage Junction Temperature	T _J , T _{stg}		-65 to +200°C	

ELECTRICAL CHARACTERISTICS (T=25°C)

Symbol	Test Conditions	2N6306		2N6307		2N6308		Unit
		Min	Max	Min	Max	Min	Max	
I _{CEV}	V _{CE} =rated V _{CB} , V _{EB} =1.5V		500		500		500	uA
I _{CEO}	V _{CE} =rated V _{CE0}		500		500		500	uA
I _{EBO}	V _{EB} =8V		1.0		1.0		1.0	mA
V _{CEO}	I _C =100mA	250		300		350		V
V _{CE(s)}	I _C =3A, I _B =0.6A		0.8		1.0		1.5	V
V _{CE(s)}	I _C =8A, I _B =2A		5.0		5.0			V
V _{CE(s)}	I _C =8A, I _B =2.67A						5.0	V
V _{BE(s)}	I _C =8A, I _B =2A		2.3		2.3			V
V _{BE(s)}	I _C =8A, I _B =2.67A						2.5	V
V _{BE(on)}	V _{CE} =5V, I _C =3A		1.3		1.3		1.5	V
h _{FE}	V _{CE} =5V, I _C =3A	15	75	15	75	12	60	-
h _{FE}	V _{CE} =5V, I _C =8A	4		4		3		-
f _T	V _{CE} =10V, I _C =0.3A, f=1.0 MHZ	5		5		5		MHZ
C _{ob}	V _{CB} =10V, f=1.0 MHZ		250		250		250	pF
t _r	V _{CC} =125V, I _C =3.0A, I _B =0.6A		0.6		0.6		0.6	uS
t _s	V _{CC} =125V, I _C =3.0A, I _B =0.6A		1.6		1.6		1.6	uS
t _f	V _{CC} =125V, I _C =3.0A, I _B =0.6A		0.4		0.4		0.4	uS



OUTSTANDING SUPPORT AND SUPERIOR SERVICES

PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix " TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix " PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Central Semiconductor manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MJ15024/WS](#) [MJ15025/WS](#) [BC546/116](#) [BC556/FSC](#) [BC557/116](#) [BSW67A](#) [HN7G01FU-A\(T5L,F,T](#)
[NJVMJD148T4G](#) [NSVMMBT6520LT1G](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE2353](#) [NTE316](#) [IMX9T110](#) [NTE63](#) [NTE65](#)
[C4460](#) [SBC846BLT3G](#) [2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA1727TLP](#) [2SA2126-E](#) [2SB1202T-TL-E](#) [2SB1204S-TL-E](#) [2SC5488A-](#)
[TL-H](#) [2SD2150T100R](#) [SP000011176](#) [FMC5AT148](#) [2N2369ADCSM](#) [2SB1202S-TL-E](#) [2SC2412KT146S](#) [2SC4618TLN](#) [2SC5490A-TL-H](#)
[2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [BC557B](#) [TTC012\(Q\)](#) [BULD128DT4](#) [JANTX2N3810](#)
[Jantx2N5416](#) [US6T6TR](#) [KSF350](#) [068071B](#)