






EPCOS Sample Kit 2015

SMT Current Sense Transformers

EE 5.0 Core Series – B82801B






www.epcos.com


Current Sense Transformers - EE 5.0 Core (SMT)

Turns ratio	Np : Ns	1 : 20	1 : 30	1 : 40	1 : 50	1 : 60
L _{min}	μH	80	180	320	500	720
Voltage-time product	V*μs	10.0	15.0	20.0	25.0	30.0
Ordering code	B82801	B0803A020	B0184A030	B0324A040	B0504A050	B0724A060
Turns ratio	Np : Ns	1 : 70	1 : 100	1 : 125	1 : 200	
L _{min}	μH	980	2000	3000	8000	
Voltage-time product	V*μs	35.0	50.0	62.5	100.0	
Ordering code	B82801	B0984A070	B0205A100	B0305A125	B0925A200	

- All values measured at +25 °C ambient temperature
- Frequency range: 50 kHz ... 1 MHz
- Sensed current: The max. primary current of 20 A causes approx. +40 °C temperature rise
- Operating temperature range: -40 °C ... +125 °C
- Tape and reel packing: 16 mm blister tape, 330 mm reel
- Packing units: 900 pcs./reel; 7200 pcs./carton




Recommended PCB layout




IND1143-FE


1:20




1:30




1:40




1:50




1:60




1:70




1:100



1:125



1:200



Important information: It is incumbent on the customer to check and decide whether a product is suitable for use in a particular application. Our products are described in detail in our data sheets. Our *Important notes* and the product-specific *Cautions and warnings* must be observed. All relevant information is available through our sales offices.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Current Transformers](#) category:

Click to view products by [EPCOS](#) manufacturer:

Other Similar products are found below :

[MP3500](#) [BV UI 302 0156](#) [45029](#) [BV EI 302 2863](#) [BV EI 303 2809](#) [BV EI 303 3060](#) [BV EI 305 2309](#) [BV EI 306 3604](#) [BV EI 481 1295](#) [BV EI 481 1325](#) [BV UI 301 0133](#) [BV UI 302 0144](#) [BV UI 302 0161](#) [BV UI 304 0019](#) [BV UI 304 0129](#) [BV UI 304 0159](#) [BV UI 304 0173](#) [TI-EF16-2X4V-4W](#) [SPCT62/40150/5AVA3CL1](#) [SPCT62/30100/5AVA1CL1](#) [SPCT62/3075/5AVA1CL3](#) [SPCT62/40150/5AVA1.5CL1](#) [SPCT62/40200/5AVA2.5CL0.5](#) [SPCT62/40300/5AVA3CL0.5](#) [CTD-KIT](#) [44013](#) [44017](#) [44021](#) [44098](#) [44101](#) [44134](#) [44171](#) [44174](#) [44178](#) [44180](#) [44248](#) [44250](#) [44278](#) [44339](#) [44340](#) [44373](#) [44375](#) [44376](#) [44378](#) [44379](#) [44436](#) [44831](#) [B82801B0925A200](#) [PA3655NL](#) [PA3828NL](#)