

## EasyView™ Light Meters

 **Choice of models for high intensity measurements**  
Up to 400,000 Lux and 40,000 Foot candles

### Features:

- Compact and rugged design features large display
- Multiple wide measuring ranges:  
Model EA30 - 40,000Fc in 4 ranges and 400,000Lux in 5 ranges  
Model EA31 - 20,000Fc in 4 ranges and 20,000Lux in 4 ranges
- Data hold freezes reading on display
- MIN/MAX readings
- Cosine and color corrected measurements
- Low battery and overrange indication
- Auto power off to save battery life
- Utilizes precision silicon photodiode sensor with 3ft coiled cable for easy storage
- Complete with built-in stand, remote sensor with protective cover, protective rubber holster, and 6 AAA batteries



### Additional features for Model EA30:

- Large display with bargraph
- Peak hold captures short light pulses to 100µSec
- Relative function for zero or difference from reference value



Specifications	Range	Resolution	Basic Accuracy
<b>EA30</b> Lux	40, 400, 4000, 40000, 400000Lux	0.01	±3%rdg + 0.5%FS
Foot candles	40, 400, 4000, 40000Fc		
<b>EA31</b> Lux	20, 200, 2000, 20000Lux	0.01	±3%rdg + 0.5%FS
Foot candles	20, 200, 2000, 20000Fc		
Dimensions	5.9 x 2.8 x 1.4" (150 x 72 x 33mm)		
Weight	8.3oz (235g)		

### Ordering Information:

- EA30** .....EasyView™ High Intensity Light Meter  
**EA30-NIST** .....EA30 with Calibration Traceable to NIST  
**EA31** .....EasyView™ Light Meter  
**EA31-NIST** .....EA31 with Calibration Traceable to NIST



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [Extech](#) manufacturer:*

Other Similar products are found below :

[I800](#) [FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)  
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)  
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)  
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)  
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#)