



Push-In Fasteners provide an inexpensive, fast, convenient method to join plastic, circuit boards, or any other thin, light-weight material. They can also be used as push in glides or as bumpers. Special designed legs provide compression and expansion to lock fastener into pre-punched holes. These fasteners are vibration, abrasion and corrosion resistant, and feature large heads for easier assembly, and can be used over and over.

MOUSER STOCK NO.	Description	Dimensions: in.					
		H	A	B	C	D	L
561-PIF37	PIF37	0.375±.015	0.636±.008	0.180±.005	0.220±.005	0.180±.005	0.875±.015
561-PIF18	PIF18	.203±.015	.230±.008	.098±.005	.156±.005	.128±.005	.365±.015
561-PIF11	PIF11	.203±.015	.208±.005	.083±.015	.140±.005	.115±.005	.320±.015

MATERIAL

• Natural nylon 6/6

X-ON Electronics

Authorized Distributor

Click to view similar products for [Screws & Fasteners](#) category:

[007638X](#) [008712F](#) [M3X6CHEESEHEAD](#) [F03-02 SUS316](#) [809704-1](#) [986619-1](#) [H1224S100](#)
[13125X](#) [142125](#) [1421NP250](#)