

## Heavy Duty Differential Pressure Manometer

**Wide range dual input**  
With multiple units and RS-232 interface

### Features:

- Dual differential inputs with internal sensors
- Wide ( $\pm 802$  inches of water) measurement range with high resolution
- Displays 8 types of pressure units: mbar, psi,  $\text{kg}/\text{cm}^2$ , mmHg, inHg, mH<sub>2</sub>O, inH<sub>2</sub>O, and atm
- Record/Recall MIN and MAX readings
- Data Hold and Auto Power off
- Zero function for offset measurements
- Basic accuracy:  $\pm 1\%$  of full scale (includes hysteresis)
- Large dual LCD display
- Metal input connections with two quick-disconnect fittings
- Built-in RS-232 PC interface with optional Data Acquisition software (407001)
- Includes 2 quick disconnect-fittings, 9V battery, protective rubber holster with stand, and carrying case



Specifications	Range	Resolution	Basic Accuracy
mbar	$\pm 2000$ mbar	1mbar	$\pm 2\%$ FS
psi	$\pm 29$ psi	0.01psi	$\pm 1\%$ FS
$\text{kg}/\text{cm}^2$	$\pm 2.040$ $\text{kg}/\text{cm}^2$	0.001 $\text{kg}/\text{cm}^2$	$\pm 1\%$ FS
mmHg	$\pm 1500$ mmHg	1mmHg	$\pm 1\%$ FS
inHg	$\pm 59.06$ inHg	0.02inHg	$\pm 1\%$ FS
mH <sub>2</sub> O	$\pm 20.40$ mH <sub>2</sub> O	0.01mH <sub>2</sub> O	$\pm 1\%$ FS
inH <sub>2</sub> O	$\pm 802.0$ inH <sub>2</sub> O	0.5inH <sub>2</sub> O	$\pm 1\%$ FS
atm	$\pm 1.974$ atm	0.001atm	$\pm 1\%$ FS
Dimensions	7 x 2.9 x 1.3" (178 x 74 x 33mm)		
Weight	12oz (350g)		

### Ordering Information:

407910 .....Heavy Duty Manometer  
407910-NIST .....407910 with NIST Certificate  
156119 .....117V AC Adaptor  
409997 .....Soft Vinyl Pouch Carrying Case

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [Extech](#) manufacturer:*

Other Similar products are found below :

[FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)  
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#)  
[CIE600](#) [TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374](#)  
[FC](#) [TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [MA610](#) [EA30-](#)  
[NIST](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#) [DIGIFLEX 400A 170MM](#) [DIGIFLEX 400A 250MM](#)