

MILAN S.r.l. a socio unico

Head Office – Export department:
 Viale Europa, 74
 20090 Cusago (MI) Italy
 T. +39 02 9039.4556-4158
 F. +39 02 9039.4551
 www.taskercables.com

Ufficio Commerciale e Centro Distribuzione
 Viale Europa 72 Strada F12
 20090 Cusago (MI) Italy
 T. +39 02 9039.0037-0059
 F. +39 02 9039.0049
 www.tasker.it

Technical Datasheet




tasker® RG 59 Flex -Coaxial Cable 75 Ω



A	B	C	D
---	---	---	---

CATEGORY
APPLICATIONS

Coaxial cable 75 Ω (See Video Catalogue)
 Premade video Cables and Broadcast.

- A:** PVC Sheath available in different color.
Outer cable Diam. Ø 6,10 (±0,10) mm.
- B:** Shielding in O.F.C. red copper braid covering 90% .
- C:** Core Insulation with transparent PE. Diam. Ø 3,70 (±0,10) mm.
- D:** Stranded O.F.C. red copper formation 7x0,20 mm.
Nom. Cross section 1x0,22 mm².

MARKING
AVAILABLE ALSO

tasker® RG59 FLEX 75Ω BROADCAST VIDEO CABLE
 RG59 BU, RG59 Extra, RG59 LSZH, RG59 Special, RG59 PUR,
 RG59 AR

CUSTOM
PRODUCTION

This product may be custom produced also in **PE**, with or without
 Metallic Armor.

Cable Properties

Conductor Resistance	75 Ω/Km
Capacity Core/Shield	67 pF/mt
Velocity of Propagation	66%
Impedance	75 Ω
Max Rated Voltage	2.000 V
Operative Temperature	-15/+70°C

Attenuation dB/100 m.

50 MHz	7,4
100 MHz	10,7
200 MHz	15,7
400 MHz	22,7
800 MHz	33,6
1000 MHz	38,0

USE	X	Indoor	Interno Edificio
Impiego		Outdoor Limited	Esterno Limitato
		Outdoor	Esterno
		Outdoor Direct Burial	Esterno Interrato

INSTALLATION	X	Fixed	Fissa
Posa	X	Restricted Mobile	Mobile Limitata
		Mobile	Mobile
		Mobile in Drag Chain	Mobile in Catena

INFORMATION	X	RoHS2 Compliant
Informazioni	X	Ver. A / 16.05.16

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Coaxial Cables](#) category:

Click to view products by [Tasker](#) manufacturer:

Other Similar products are found below :

[89880-003-1000](#) [633948-877-1000](#) [CY2389-000](#) [8213-010-1000](#) [8221-010-U1000](#) [8233-010-1000](#) [88281-010-500](#) [1322R-010-1000](#) [177799-000](#) [1807A-B59-U1000](#) [9167-010-1000](#) [9251-010-1000](#) [9275-010-U1000](#) [935240-000](#) [9659-010-1000](#) [980704-001](#) [CF2823-000](#) [33312-010-500](#) [CZ1589-000](#) [5022W0809-0CS3263](#) [10610-4-4](#) [EF8108-000](#) [1673B TIN100](#) [672525-001](#) [144517-000](#) [8-1616396-1](#) [8263-010-U1000](#) [8263 010U500](#) [8268-010-500](#) [8262 010U1000](#) [7915A 009U1000](#) [5024A1311-0](#) [TRC-75-1](#) [1281S5 010250](#) [1281S5 000250](#) [1530A 010U1000](#) [1505A 0081000](#) [9248 010U1000](#) [CO-142BNCX200-001](#) [7809WB 010500](#) [9244 0101000](#) [1694A 0081000](#) [9204 0101000](#) [8241F J5C1000](#) [1530A 0101000](#) [1674A TIN50](#) [7915A 0091000](#) [7915A 010500](#) [TWCH-78-2](#) [TWC-78-1](#)