

**POWER EXTENSION SOCKET****NEW****MINI USB CHARGER****P/No. A13-234****Features:**

- Rating : Input : 12~24V DC. USB output : 5V 2.4A / 1A max
- **A13-234A** : LED illuminated frame
- **A13-234B** : black frame
- **A13-234C** : laser-engraving legend frame
- Snap in USB charger
- Reversed polarity protection
- **A13-234AUW-W1** : 5V 2.4A max, blue LED illuminated frame, 2.5A glass tube fuse max
- **A13-234B-W1** : 5V 1A max, black, without LED, 1.5A glass tube fuse max
- **A13-234CUB-W1** : 5V 2.4A max, laser-engraving legend frame, 2.5A glass tube fuse max
- **A13-234CUB-W2** : 5V 1A max, laser-engraving legend frame, 1.5A glass tube fuse max
- **A13-234CUB-W3** : 5V 2.4A max, laser-engraving legend frame, without fuse
- Assemble the power convert and fuse #R3-48 with 0.185"SQ terminal
- Optional accessories : Holder #PR18-B5
- Mounting hole :  $\varnothing$  20.2 mm
- Size: 22.9 (D) x 24.8 (H) mm (wire harness not included)

**A13-234AUW-W1****DUAL USB CHARGER****P/No. A13-230****Features:**

- Rating : Input : 12~24V DC. USB output : 5V 2.1A+2.1A max., 2 ports
- Screw in USB charger with dust-proof cover
- Reversed polarity protection
- Backlighting power indication shown per laser-engraving legend on panel
- Customized legends on the dust-proof cover and on the laser-engraving panel are available
- Optional accessories : single / dual / triple mounting panel and surface mount case
- Mounting hole :  $\varnothing$  29.0 mm
- Size : 36.8 (D) x 50.4 (H) mm

**DUAL USB CHARGER****P/No. A13-236****Features:**

- Rating : Input : 12~24V DC. USB output : 5V 2.1A + 2.1A max., 2 ports
- Snap in USB charger with dust-proof cover
- **A13-236AU-BB3** : 0.250" quick terminals
- **A13-263BU-BB3** : 22AWG wire
- Reversed polarity protection
- Backlighting power indication shown per laser-engraving legend on panel
- Customized legends on the dust-proof cover and the laser-engraving panel are available
- Optional accessories: Panel #PR18-E2/3/4-B
- Mounting hole : 36.6 (W) x 21.2 (H) mm
- Size : 49.0 (L) x 24.2 (W) x 49.1 (H) mm



\*All the specifications are subject to change without notice.



Headquarters:  
TEL : 886-6-2532181  
FAX : 886-6-2532633

Taipei Branch Office:  
TEL : 886-2-25014062-4  
FAX : 886-2-25040685

China Factory:  
TEL : 86-752-3897988  
FAX : 86-752-3897986  
www.shinchin-sci.com

Hong Kong Branch:  
TEL : 852-27939773  
FAX : 852-27939830

Indonesia Factory:  
TEL : 62-24-7627048  
FAX : 62-24-7627047

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Standard Circular Connector](#) category:*

*Click to view products by [SCI manufacturer](#):*

Other Similar products are found below :

[C015](#) [10F006](#) [001](#) [1](#) [5M2530B10P](#) [600259N006](#) [600273N007](#) [600432N009](#) [6280-2PG-519](#) [6280-3PG-311](#) [6280-3SG-311](#) [6280-7SG-3DC](#)  
[6280-7SG-522](#) [6282-5PG-311](#) [6282-6PG-519](#) [6282-8SG-311](#) [6283-11](#) [6283-15](#) [6290](#) [6382-2PG-311](#) [6382-2PG-3DC](#) [6382-2SG-321](#) [6382-2SG-3DC](#) [6382-4SG-516](#) [67-03E20-37P](#) [680-SMG](#) [681-PMG](#) [CXS3102A14S2P](#) [CXS3102A181S](#) [CXS3106A14S6S](#) [MB12P-1](#) [MB12R-6](#)  
[7251-2PG-300](#) [7251-2SG-300](#) [7251-4PG-300](#) [7251-4SG-300](#) [7251-5PG-300](#) [7251-5SG-300](#) [7251-6SG-300](#) [7251-7PG-300](#) [7251-8PG-300](#)  
[7271-6SG-300](#) [7282-3PG-300-CH3](#) [73000005663](#) [75-190216-08S](#) [75-190218-10P](#) [75-474118-10P](#) [75-474618-01S](#) [75-474620-07P](#) [799539-000](#) [MI8-SE](#) [80-190222-18P](#) [805-005-07NF11-19PC](#)