



| | |
|-------------------------------|---------------------------------------|
| Type Designation | 4014 |
| Designation IEC | LR14 |
| System | Zn-MnO ₂ (Alkaline) |
| Shelf Life (Coding)* | 5 years |
| Nominal Voltage [V] | 1.5 |
| Typical Capacity C [mAh] | 7800 (discharge with high-resistance) |
| Permissible Temperature Range | - 10 °C ... 50 °C |
| Weight, approx. [g] | 66 |
| Volume [ccm] | 26.5 |

Dimensions [mm]

min: max:

| | | |
|---|------|------|
| Ø | 24.9 | 26.2 |
| A | - | 50.0 |
| B | 48.6 | - |
| C | 13.0 | - |
| E | - | 0.9 |
| F | - | 7.5 |
| G | 1.5 | - |

Typical Capacities (at 20°C)

| Discharge Type | Load | End Voltage[V] | 1,0 | 0,9 |
|-------------------------------------|-------|----------------|-------|-------|
| 4M/H,8H/D,7D/W Portable Lighting | 3.9 Ω | Time [m] | 1110 | 1276 |
| | | Capacity [Ah] | 5,73 | 6,46 |
| | | Energy [Wh] | 6,97 | 7,71 |
| Discharge Type | Load | End Voltage[V] | 0,9 | 0,8 |
| 1H/D,7D/W Toys | 3.9 Ω | Time [h] | 22,12 | 24,19 |
| | | Capacity [Ah] | 6,32 | 6,79 |
| | | Energy [Wh] | 7,20 | 7,61 |
| Discharge Type | Load | End Voltage[V] | 1,0 | 0,9 |
| 1H/D,7D/W Tape Recorders | 6.8 Ω | Time [h] | 35,37 | 39,28 |
| | | Capacity [Ah] | 6,35 | 6,92 |
| | | Energy [Wh] | 7,68 | 8,23 |
| Discharge Type | Load | End Voltage[V] | 1,0 | 0,9 |
| 4H/D,7D/W Transistor Radios | 20 Ω | Time [h] | 113,4 | 122,9 |
| | | Capacity [Ah] | 7,10 | 7,55 |
| | | Energy [Wh] | 8,94 | 9,38 |

No publication or circulation of data to third parties without consent of VARTA Consumer Batteries

* In consideration of typical loss of capacity at storage and application.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Battery Packs](#) category:

Click to view products by [Varta](#) manufacturer:

Other Similar products are found below :

[2280309-1](#) [R101-B](#) [4114 210 501](#) [4120 210 501](#) [4600 726 406](#) [4610 726 406](#) [312G-U1](#) [55615703012](#) [3LR12](#) [4103 210 392](#) [4103 210 394](#)
[4106 210 392](#) [4106 210 394](#) [4223 210 501](#) [4606 726 406](#) [4607 726 406](#) [ZA13](#) [LR03/AAA/MN2400\(K4\)](#) [LR03 MAXELL S4](#) [LR1130](#)
[MAXELL B10](#) [LR14-MN1400-C K2](#) [LR1/910A](#) [LR41 MAXELL B10](#) [LR43](#) [LR43 MAXELL B10](#) [LR6 MAXELL S4](#) [11012](#) [E23A](#) [E90](#)
[625302](#) [625304](#) [637871](#) [638006](#) [6LF22/9V/MN1604\(K1\)C&B](#) [6LF22/9V/MN1604 PLUS](#) [6LR61](#) [SR626SW MAXELL](#) [SR920SW](#)
[MAXELL](#) [7K67 J](#) [55615303059](#) [GP14A S2](#) [GP15E](#) [GP1604GLF-2UE1](#) [GP 1604 ULTRA PLUS](#) [23733](#) [10 ET](#) [675 ET](#) [11A B5](#) [A544](#) [A76-](#)
[U10](#)