
The Flashni is an audible and visual device which requires one single installation point. This greatly reduces installation costs and is less obtrusive than two separate devices. Versions are available with the sounder and beacon linked, or with separate terminals for independent operation.




## **Technical Specification**

Voltage	9 - 15Vdc (12V version) 18 - 28Vdc (24V version) (*1)
Current	110mA 12V version (Typical Tone 5) 68mA 24V version (Typical Tone 3)
Sound Output	103dB(A) 12V version (Typical Tone 5) 101dB(A) 24V version (Typical Tone 3)
Tones	Pre-set to tone 5 (12v) Pre-set to tone 3 (24v) (versions are available with user selectable tones)
Flash Power	0.7j
Flash Rate	1Hz
Volume Control	10dB
Monitoring	Reverse polarity
Temperature	- 10°C to + 55°C
Protection	IP54 (s)* IP65 (d)*
Construction	ABS, PC lens
Weight	0.33Kg
Colours	Red or white
Lens Colour	Red, amber, blue, green or clear
(s)* Shallow Base	•







**Features** 

(d)\* Deep / U Base

- High output sounder beacon
- 12V, 24V and mains module option
- Choice of lens colour options
- Automatic sounder synchronisation

### Reference

FL/RL/R/S SWITCH FL/RL/R/D SWITCH FL/AL/W/D SWITCH FL/RL/R/S 12V SND5 640204FULL-0067 FL/RL/W/S 12V SND5 640202FULL-0039

Catalogue No. 640025FULL-0061X 640031FULL-0111X 640024FULL-0060X

For full list of part numbers, turn to page 61

## **Benefits**

- Up to 103dB(A) with built in Xenon flash
- For use on Fire, Industrial or Security systems
- Suitable for a variety of application
- Improved tone clarity, reducing confusion

### Description

Flashni Sounder/Beacon, Red lens, Red body, Deep base, Tone select switch. Flashni Sounder/Beacon, Amber lens, White body, Deep base, Tone select switch Flashni 12V Sounder/Beacon, Clear lens, White body, Deep base, tone 5

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Fulleon manufacturer:

Other Similar products are found below :

AS/M/SB/9-60V/R/RL AC/W/S/BB FB/024/R AS/M/S/115/230/R SYHO/R FL/BL/W/D/12V FB/230/G FL/AL/W/S AF/W/S/VC CFB6D24 1320-24 531036FULL-0073 FL/SV/RL/R/D FL/AL/W/D/12V 666156FULL-1101X ROLP/R/MAINS BASE ROLP/SV/W/S ROLP/SV/W/D AP/W/SWITCHED/VC ROLP/SV/R/S