



Price\* : 84.48 GBP



### Main

Range	Spacial
Accessory / separate part category	Mounting accessory
Application	Multi-purpose Modular distribution application
Product or component type	Chassis
Device short name	DLA
For enclosure nominal dimensions	H: -
Mounting location	Front of enclosure
Range compatibility	Spacial CRN Spacial S3D Spacial S3X Thalassa PLM
Device composition	1 chassis structure 2 finish cover 1 neutral/earth strip 2 x 16 mm <sup>2</sup> 5 x 6 mm <sup>2</sup> 3 front panels with 35 mm DIN rail 1 plain front panel with mounting plate
Quantity per set	Set of 1

### Complementary

Material	Self-extinguishing insulating for front panel Steel for chassis structure and rails
Colour	Front panel : grey RAL 7035
Fixing mode	By fixing element - on front with supports location
Adjustment	In height from 40 to 85 mm for DIN rail
Number of horizontal rows	4
Total number of 18 mm modules	66
Type of front plate	Plain and cut-out plates
Number of cut-out	4 cut-outs

Height	680 mm
Width	460 mm

### Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 1511 - Schneider Electric declaration of conformity <a href="#">Schneider Electric declaration of conformity</a>
REACH	Reference not containing SVHC above the threshold <a href="#">Reference not containing SVHC above the threshold</a>
Product environmental profile	Available <a href="#">Product Environmental Profile</a>
Product end of life instructions	Need no specific recycling operations

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Electrical Enclosures](#) category:*

*Click to view products by [Schneider](#) manufacturer:*

Other Similar products are found below :

[120-902](#) [120-905](#) [120-403](#) [120-475](#) [120-901](#) [127-410](#) [130-007](#) [130-504](#) [130-506](#) [MR-25L+](#) [30-8739](#) [PIP-11774SCREW](#) [30-9715](#) [MR-25LW+](#) [110-407](#) [111-004](#) [111-008](#) [110-402](#) [110-901](#) [110-907](#) [111-002](#) [110-406](#) [110-910](#) [110-404](#) [110-409](#) [110-410](#) [120-405](#) [106-009](#) [106-505](#) [105-401](#) [106-006](#) [104-406](#) [137-002](#) [105-405](#) [111-005](#) [127-909](#) [106-502](#) [130-475](#) [130-503](#) [127-401](#) [106-010](#) [127-455](#) [127-475](#) [110-903](#) [R260-180-300](#) [9511020](#) [9822029](#) [9820014](#) [P61603000P](#) [9823009](#)