

ENCASED TRANSFORMERS FOR ELECTRIC TOOLS

PFN

Purpose:

PFN transformers, as separation portable devices, are dedicated for powering electric tools or other similar appliances for constant or intermittent work.

Technical data:

Rated voltage PRI: 230V 50Hz
 Rated voltage SEC: 230V
 Rated power for intermittent work 33%: P33 - see table below
 Rated power for constant work: Pn - see table below
 Ambient temperature: ta25°C
 Insulation class: II lub II+PE (with the continuity of protection circuit)
 Protection grade: IP44
 Manufactured in compliance with: PN-EN 61558-1:2009,
 PN-EN 61558-2-4:2009

Transformer construction:

- solid metal IP44 housing
- 2,2m powering cable with 250/16A* plug
- output 250V/16A IP44* socket
- thermal protection fuse on primary winding with a button (fuse current according to table)
- winding thermal insulation class F (155 C)

*2 or 3 contact plugs and sockets mounted in standard. Other performances on customers request.



Drawing 1



Drawing 2

Type	Insulation class	P33 [VA]	Imax [A]	Pn [VA]	In [A]	Fuse current[A]	Weight [kg]	Dimensions [mm]
PFN 2400/1500	II	2400	11	1500	6,5	12	20,0	Drawing1
PFN2401/1501	II+PE	2400	11	1500	6,5	12	20,0	Drawing1
PFN3500/2300	II	3500	15	2300	10,0	16	26,0	Drawing1
PFN3501/2301	II+PE	3500	15	2300	10,0	16	26,0	Drawing1
PFN4200/2800	II	4200	18	2800	12,0	25	33,6	Drawing2
PFN4201/2801	II+PE	4200	18	2800	12,0	25	33,6	Drawing2

The example of 33% intermittent work:
 Multiple cycles - 5min of work and 10min of break.

Type	Art. No.:	Notices
PFN 2400/1500 230/230V	16152-9988	1 socket SEC
PFN 2400/1500 230/230V 3GN		3 sockets SEC
PFN 2401/1501 230/230V	16152-9989	1 socket SEC
PFN 2401/1501 230/230V 3GN		3 sockets SEC
PFN 3500/2300 230/230V	16152-9987	1 socket SEC
PFN 3500/2300 230/230V 3GN		3 sockets SEC
PFN 3501/2301 230/230V	16152-9986	1 socket SEC
PFN 3501/2301 230/230V 3GN		3 sockets SEC
PFN 4200/2800 230/230V 3GN	16152-9983	3 sockets SEC
PFN 4201/2801 230/230V 3GN	16152-9984	3 sockets SEC

Because of the constant development of product construction and changes concerning technical requirements, Breve-Tufvassons Company reserves the right to change the parameters mentioned above.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Current Transformers](#) category:

Click to view products by [Breve Tufvassons](#) manufacturer:

Other Similar products are found below :

[MP3500](#) [BV UI 302 0156](#) [45029](#) [BV EI 302 2863](#) [BV EI 303 2809](#) [BV EI 303 3060](#) [BV EI 305 2309](#) [BV EI 306 3604](#) [BV EI 481 1295](#) [BV EI 481 1325](#) [BV UI 301 0133](#) [BV UI 302 0144](#) [BV UI 302 0161](#) [BV UI 304 0019](#) [BV UI 304 0129](#) [BV UI 304 0159](#) [BV UI 304 0173](#) [TI-EF16-2X4V-4W](#) [SPCT62/40150/5AVA3CL1](#) [SPCT62/30100/5AVA1CL1](#) [SPCT62/3075/5AVA1CL3](#) [SPCT62/40150/5AVA1.5CL1](#) [SPCT62/40200/5AVA2.5CL0.5](#) [SPCT62/40300/5AVA3CL0.5](#) [CTD-KIT](#) [44013](#) [44017](#) [44021](#) [44098](#) [44101](#) [44134](#) [44171](#) [44174](#) [44178](#) [44180](#) [44248](#) [44250](#) [44278](#) [44339](#) [44340](#) [44373](#) [44375](#) [44376](#) [44378](#) [44379](#) [44436](#) [44831](#) [B82801B0925A200](#) [PA3655NL](#) [PA3828NL](#)