



# Uninterruptible power supply | 1000VA | 600W

Product code: 53903

High quality uninterruptible power supplies ensure stable operation of connected electronic devices even in the case of power failure.

Power: 600W

Output sockets: 1 x IEC, 3 x SCHUKO

## UPS

Qoltec emergency power system UPS offline is a modern and economical device, which provides emergency power to connected loads when the input power source or mains power fails. UPS protects connected devices from power disruption, voltage spike and eliminates possible damage in case of mains power overvoltage. It also protects connected loads from overloads and short circuit.

Qoltec UPS offline meets everyone's requirements, who are looking for device, which protects connected loads from instability of the mains frequency. Thanks to high quality and wide operating range it is perfect solution for people who want to have ensured the continuity of operation of computers and other peripheral devices in home, enterprise, educational institutions and government offices. UPS offline is also indispensable to power central heating pump.

## TECHNICAL DATA

USABLE POWER	600 W
RATED CAPACITY	1000 VA
POWER FACTORY	0,6
LOAD TYPE	Personal computer and other PC peripheral devices
AC VOLTAGE RANGE	140Vac ~ 290Vac / 5Vac
AC FREQUENCY	40Hz ~ 70Hz / 1Hz
OUTPUT RANGE (LINE)	220Vac - 230Vac / 10%
OUTPUT FREQUENCY (LINE)	40Hz ~ 70Hz / 1Hz
OUTPUT VOLTAGE (BATTERY)	220Vac - 230Vac / 5%

<b>OUTPUT FREQUENCY (BATTERY)</b>	50Hz - 60Hz / 1Hz
<b>TRANSFER TIME</b>	10ms
<b>OUTPUT SOCKETS</b>	1 x IEC 3 x SCHUKO
<b>BACKUP TIME</b>	> 6 min (half charge)
<b>BUILT-IN BATTERY</b>	2x12V / 7Ah
<b>CHARGING TIME</b>	8 hrs (to fully charged)
<b>STORAGE TEMPERATURES</b>	-15°C to 45°C
<b>OPERATING TEMPERATURE</b>	0°C to 40°C
<b>RELATIVE HUMIDITY</b>	0% - 90%
<b>SAFETY</b>	Surge protection Overload protection Short Circuit Protection Under/ Overvoltage Protection
<b>ADDITIONAL INFORMATION</b>	Auto charging Charging in UPS OFF Mode Sound signal LEDs
<b>PACKAGE CONTENTS</b>	UPS with built-in power cable (1xSchuko) 1.2m User manual Warranty card
<b>NOISE</b>	35dB ( 1 meter from front panel)
<b>NETWORK PROTECTION</b>	RJ45 / 11 surge protector (Optional)
<b>COMMUNICATION INTERFACE</b>	Intelligent RS-232 / USB (Optional)
<b>DIMENSIONS</b>	341 x 122 x 195 mm
<b>WEIGHT</b>	8.5 kg
<b>WARRANTY</b>	24 months
<b>RUNTIME (100W)</b>	30 min
<b>EAN CODE</b>	5901878539034

<b>SHORT CIRCUIT</b>	Auto protection. Output shuts off and the buzzer beeps continuously.
<b>OVERLOAD</b>	110% 120%, buzzer beeps. UPS switches off within 5 minutes; >120% buzzer beeps continuously, UPS immediately turns off
<b>BATTERY PROTECTION</b>	Auto protection. The UPS auto shutdown when battery voltage is low or high.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Switching Power Supplies](#) category:*

*Click to view products by [QOLTEC](#) manufacturer:*

Other Similar products are found below :

[70841011](#) [73-551-0005](#) [MDPS](#) [AAD600S-4-OP](#) [R22095](#) [MQB02002](#) [BFE05SX-U](#) [BTJ716K01D-7067](#) [KD0204](#) [9021](#) [S-15F-12](#) [LDIN100150](#)  
[LPM000-BBAR-01](#) [LPX17S-C](#) [FDC40-24S12](#) [FP80](#) [FRV7000G](#) [22929](#) [CQM1IA121](#) [40370121900](#) [VI-NU2-EM](#) [VI-PU22-EXX](#) [40370121910](#)  
[LDIN5075](#) [432703037161](#) [WRB01X-U](#) [LPX140-C](#) [08-30466-1040G](#) [09-160CFG](#) [70841004](#) [70841025](#) [LPM000-BBAR-05](#) [LPM000-BBAR-08](#)  
[LPM124-OUTA1-48](#) [LPM000-BBAR-07](#) [LPM109-OUTA1-10](#) [LPM616-CHAS](#) [08-30466-1055G](#) [08-30466-2175G](#) [DMB-EWG](#) [TVQF-1219-18S](#)  
[6504-226-2101](#) [CQM1IPS01](#) [XPFM201A+](#) [MAP55-4003G](#) [73-554-0320I](#) [MAP80-4000G](#) [LFP300F-24-TY](#) [SMP21-L20-DC24V-5A](#) [VI-MUL-ES](#)