



Uninterruptible Power Supply | Monolith | 850VA | 510W | 2xUSB

Product code: 53966

High quality uninterruptible power supplies ensure stable operation of connected electronic devices even in the case of power failure.

Power: 510W

Sockets: 3 x SCHUKO Backup and Surge Protection

3 x SCHUKO Surge Protection

2 x USB (5V, 2A)

TECHNICAL DATA

USABLE POWER	510 W
RATED CAPACITY	850 VA
POWER FACTORY	0.6
LOAD TYPE	Personal computer and other peripheral devices
AC VOLTAGE RANGE	140Vac ~ 290Vac
AC FREQUENCY	50Hz 10%
OUTPUT RANGE (LINE)	220Vac 10%
OUTPUT FREQUENCY (LINE)	50Hz 10%
OUTPUT VOLTAGE (BATTERY)	220Vac ~ 230Vac 5%
OUTPUT FREQUENCY (BATTERY)	50Hz - 60Hz 1Hz
OUTPUT SOCKETS	3 x SCHUKO Backup and Surge Protection 3 x SCHUKO Surge Protection 2 x USB (5V, 2A)
BACKUP TIME	10 - 20 min
BUILT-IN BATTERY	1 x 12V/8Ah
CHARGING TIME	8h to reach 90% of capacity
STORAGE TEMPERATURES	-15°C to 45°C
OPERATING TEMPERATURE	20°C to +40°C
ENVIRONMENT HUMIDITY	0% - 95%

RELATIVE HUMIDITY

0% - 90%

SAFETY

Overload protection
Short Circuit Protection
Overheat Protection
High / Low Voltage Protection
Input fuses Protection

USAGE

Home and office applications

ADDITIONAL INFORMATION

2 USB ports
Note: Uninterruptible Power Supplies are not intended for use with medical devices, including life support or health equipment.

PACKAGE CONTENTS

UPS
Power cable (1 x SCHUKO) 1.2m
User manual

NOISE

Less than 40dB

DIMENSIONS

185 x 280 x 95 mm

WEIGHT

6.5 kg

WARRANTY

24 months

WAVE FORM

Simulated sine wave

FUNCTIONS

Microprocessor - based digital control
Automatic voltage regulator
Alarm with configuration capability
Power on self-test
Auto restart when mains power is restored
Cold start
Simulated sine wave output
Intelligent battery management
Automatic charging in OFF mode

EAN CODE

5901878539669

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Switching Power Supplies](#) category:

Click to view products by [QOLTEC](#) manufacturer:

Other Similar products are found below :

[70841011](#) [73-551-0005](#) [MDPS](#) [AAD600S-4-OP](#) [R22095](#) [MQB02002](#) [BFE05SX-U](#) [BTJ716K01D-7067](#) [KD0204](#) [9021](#) [S-15F-12](#)
[LDIN100150](#) [LPM000-BBAR-01](#) [LPX17S-C](#) [FDC40-24S12](#) [FP80](#) [FRV7000G](#) [22929](#) [CQM1IA121](#) [40370121900](#) [VI-NU2-EM](#) [VI-PU22-](#)
[EXX](#) [40370121910](#) [LDIN5075](#) [432703037161](#) [WRB01X-U](#) [LPX140-C](#) [08-30466-1040G](#) [09-160CFG](#) [70841004](#) [70841025](#) [LPM000-](#)
[BBAR-05](#) [LPM000-BBAR-08](#) [LPM124-OUTA1-48](#) [LPM000-BBAR-07](#) [LPM109-OUTA1-10](#) [LPM616-CHAS](#) [08-30466-1055G](#) [08-30466-](#)
[2175G](#) [DMB-EWG](#) [TVQF-1219-18S](#) [6504-226-2101](#) [CQM1IPS01](#) [XPFM201A+](#) [73-554-0320I](#) [MAP80-4000G](#) [LFP300F-24-TY](#) [SMP21-](#)
[L20-DC24V-5A](#) [VI-MUL-ES](#) [08-30466-0065G](#)