

## High Resolution Micro-Ohm Meter

**Precision meter provides resolution down to  $1\mu\Omega$**   
Using 4-wire Kelvin clip test leads

### Features:

- 6 ranges with 3 sub-ranges in each current range
- Measurement of resistive and inductive materials
- Auto or Manual ranging
- High resolution to  $1\mu\Omega$
- 5-Digit backlit LCD
- Built-in comparator for Hi/Lo resistance testing with 20 sets of prestored values
- Store/Recall up to 3000 measurements
- 10A maximum test current
- Cable length measurement (feet or meters)
- PC interface
- Complete with 4-wire cables with Kelvin clip connectors, rechargeable Li-Polymer battery, AC adapter/charger, software and USB cable, and soft carrying case



Meter includes accessories all packaged in a convenient soft pouch case



Specifications	Range	Resolution	Current	Accuracy (%rdg)
Resistance	60mΩ	1μΩ	10A	±(0.25% + 25μΩ)
	600mΩ	10μΩ	1A	±(0.25% + 250μΩ)
	6Ω	100μΩ	100mA	±(0.25% + 2.5mΩ)
	60Ω	1mΩ	10mA	±(0.25% + 25mΩ)
	600Ω	10mΩ	1mA	±(0.25% + 250mΩ)
	6kΩ	100mΩ	100μA	±(0.75% + 3Ω)
Power	Rechargeable Li-Polymer Battery			
Dimensions/Weight	10.1 x 6.1 x 2.2" (257 x 155 x 57mm)/ 2.6lb (1160g)			

### Ordering Information:

- UM200** .....Precision Micro-Ohm Meter  
**UM200-NIST** .....Precision Micro-Ohm Meter with Certificate Traceable to NIST  
**UM200-KTL** .....Replacement Kelvin Test Leads

# X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Measuring Tools](#) category:*

*Click to view products by [Extech](#) manufacturer:*

Other Similar products are found below :

[G336](#) [M225203-01](#) [G426](#) [G1333](#) [G1327](#) [G1154](#) [G1150](#) [G1152](#) [G1157](#) [G1153](#) [G1155](#) [G1009](#) [1051-03](#) [121010D](#) [121050D](#) [25541](#) [8255](#) [NF-221200130](#) [20323](#) [20363](#) [20365](#) [20368](#) [20516](#) [G800](#) [G1229](#) [1051-02](#) [1051-04](#) [1051-05](#) [1056-01](#) [1056-03](#) [LXA-112-012](#) [1100](#) [1125](#) [D1014D](#) [D1020D](#) [D1032Q](#) [D1033Q](#) [1150D](#) [1200](#) [121010GF](#) [121020D](#) [121030D](#) [121050GF](#) [31439 2](#) [33232](#) [UT107](#) [1500](#) [15922](#) [15923](#) [15924](#)