

Key Features

- Hinged mount
- Tuned to quad band GSM frequencies
- Robust construction
- Omnidirectional
- RoHS compliant



General Description

The Siretta Delta 7B is a range of omnidirectional, direct connect antennas tuned to perform on GSM / GPRS networks.

Vertically polarized, they are suitable for many of today's machine to machine and communication applications such as telemetry, remote monitoring and mesh networking applications.

Additional Considerations

- Offers widest range of mounting choices via knuckle and swivel connector
- Optimised for quad band GSM / GPRS
- Over moulded whip to ensure durability in the field
- Provides good 300° transmission / reception coverage
- Meets all EU compliance criteria for electronic goods

Rev 1.0

Key Specifications - Electrical

Operating temperature range:	-20 to 65 °C
Storage temperature range:	-30 to 75°
Impedance:	50 ohm
Gain:	1dBi (cellular)
VSWR:	<2.0:1
Operating frequencies:	850, 900, 1800, 1900MHz
Polarization:	Vertical
Radiating element:	¼ wave omni directional dipole
Radiation pattern:	Omnidirectional
Return loss:	-10dB max

Key Specifications - Mechanical

Dimensions:	110mm x 10mm
Connector:	SMA male
Mounting method:	Direct connect

Ordering Details:

Part Number	Description
DELTA7B/x/SMAM/S/S/11	Quad Band GSM/GPRS Hinged mount Antenna with SMA Male Connector

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [SIRETTA](#) manufacturer:

Other Similar products are found below :

[ALPHA4A/5M/SMAM/S/S/26](#) [DELTA5A/X/SMAM/S/S/17](#) [OSCAR17/X/TNC/S/S/19](#) [DELTA5A/X/BNCM/S/S/17](#) [SNYPER-LTE-SPECTRUM](#) [ASMA2000F058L13](#) [ASMA2000C058L13](#) [TANGO14/5M/LL/SMAM/S/S/24](#) [TANGO1/1M/FMEF/S/S/4](#) [ASME500F058L13](#) [TANGO3/0.5M/SMAM/S/S/31](#) [TANGO40/X/NTYPEF/S/S/32](#) [QUARTZ-W22-LTE\(EU\)+ACC](#) [ASMA500B174L13](#) [31557](#) [ECHO40/0.1M/UFL/S/S/32](#) [MIKE1A/5M/FMEF/S/S/20](#) [QUARTZ-W22-UMTS\(EU\)+ACC](#) [TANGO11A/2.5M/SMAM/S/S/19](#) [ASMA500F058L13](#) [ZETA-N-UMTS](#) [ECHO11/0.2M/IPEX/S/S/12](#) [ASMA300E174L13](#) [ASMA1000F058L13](#) [DELTA19/X/SMAM/S/S/35](#) [ASMA2000E058L13](#) [ASMZG300F058L13](#) [MIKE3A/5M/SMAM/S/S/17](#) [TANGO15/3M/SMAM/SMAM/S/S/24](#) [TANGO20/3M/SMAM/S/S/26](#) [ASMZG500A058L13](#) [ASMZG1500F058L13](#) [ALPHA1A/2.5M/SMAM/S/S/11](#) [OSCAR40/10M/LL/SMAM/S/S/33](#) [TANGO11A/5M/LL/SMAM/S/S/19](#) [TANGO29/1M/SMAM/RP/S/35](#) [ASME2000F058L13](#) [ASMK015X174S11](#) [LC300-N2-GPRS](#) [DELTA6A/X/SMAM/S/S/11](#) [MIKE1A/2.5M/FMEF/S/S/20](#) [ASMZG1000F058L13](#) [OSCAR41/X/NTYPEF/S/S/29](#) [TANGO22/3M/SMAM/SMAM/SMAM/26](#) [OSCAR420/0.4M/NTYPEF/S/S/19](#) [ASMK010X174S11](#) [ZETA-N2-GPRS](#) [ADAPT/SMAM/RP](#) [OSCAR18/X/NF/S/S/22](#) [TANGO14/3M/SMAM/S/S/24](#)