



Site-Flex RF Field Test Cables

Phase Stable & Ruggedized

- Rugged Construction for Field Use
- Stainless Steel Anti-Torque Connectors
- Phase & Amplitude Stable Cable
- Low VSWR, Low Insertion Loss
- Op. Temp -65C to 125C
- RoHS Compliant
- Ideal for Handheld RF & Microwave Analyzers
- Extended Frequency Solutions Available



ConductRF's Site-Flex RF Field Test Cables have been designed to support Handheld RF & Microwave Analyzers. The ruggedized construction includes anti-torque connectors that are firmly attached to the cables external armor. Crush resistant SF series cable can withstand 1,200lbs/sq.in. Additional configurations and lengths are available on request.

ConductRF #	End 1	End 2	Length	Operating Frequency	In. Loss Max	VSWR Max	Phase Stability	Amplitude Stability	Keysight Equivalent
SF09G-N1N1-F05	Type-N Male	Type-N Male	5ft	DC to 9GHz	2.521dB	1.20:1	± 1.5°	±0.1dB	N9910X-810
SF09G-N1NF-F05	Type-N Male	Type-N Female	5ft	DC to 9GHz	2.521dB	1.20:1	± 1.5°	±0.1dB	N9910X-811
SF09G-N1N2-F05	Type-N Male	Type-N R/A Male	5ft	DC to 9GHz	2.521dB	1.20:1	± 1.5°	±0.1dB	ConductRF Only
SF09G-N1N1-F12	Type-N Male	Type-N Male	12ft	DC to 9GHz	7.121dB	1.20:1	± 1.5°	±0.1dB	N9910X-812
SF09G-N1NF-F12	Type-N Male	Type-N Female	12ft	DC to 9GHz	7.121dB	1.20:1	± 1.5°	±0.1dB	N9910X-813
SF09G-N1N2-F12	Type-N Male	Type-N R/A Male	12ft	DC to 9GHz	7.121dB	1.20:1	± 1.5°	±0.1dB	ConductRF Only
SF18G-N1N1-1M0	Type-N Male	Type-N Male	1M	DC to 18GHz	2.664dB	1.30:1	± 2.0°	±0.1dB	N9910X-701
SF18G-N1NF-1M0	Type-N Male	Type-N Female	1M	DC to 18GHz	2.664dB	1.30:1	± 2.0°	±0.1dB	N9910X-700
SF18G-N1N2-1M0	Type-N Male	Type-N R/A Male	1M	DC to 18GHz	2.664dB	1.30:1	± 2.0°	±0.1dB	ConductRF Only
SF18G-N1N1-F05	Type-N Male	Type-N Male	5ft	DC to 18GHz	3.897dB	1.30:1	± 2.0°	±0.1dB	ConductRF Only
SF18G-N1NF-F05	Type-N Male	Type-N Female	5ft	DC to 18GHz	3.897dB	1.30:1	± 2.0°	±0.1dB	ConductRF Only
SF18G-N1N2-F05	Type-N Male	Type-N R/A Male	5ft	DC to 18GHz	3.897dB	1.30:1	± 2.0°	±0.1dB	ConductRF Only
SF07G-N1D1-F05	Type-N Male	Din 7/16 Male	5ft	DC to 7GHz	2.164dB	1.30:1	± 1.5°	±0.1dB	N9910X-814
SF07G-N1DF-F05	Type-N Male	Din 7/16 Female	5ft	DC to 7GHz	2.164dB	1.30:1	± 1.5°	±0.1dB	ConductRF Only
SF07G-N1D1-F12	Type-N Male	Din 7/16 Male	12ft	DC to 7GHz	4.921dB	1.30:1	± 1.5°	±0.1dB	N9910X-815
SF07G-N1DF-F12	Type-N Male	Din 7/16 Female	12ft	DC to 7GHz	4.921dB	1.30:1	± 1.5°	±0.1dB	ConductRF Only
SF18G-N1T1-F05	Type-N Male	TNC Male	5ft	DC to 18GHz	3.897dB	1.30:1	± 2.0°	±0.1dB	N9910X-705
SF18G-N1TF-F05	Type-N Male	TNC Female	5ft	DC to 18GHz	3.897dB	1.30:1	± 2.0°	±0.1dB	N9910X-704
SF18G-N1S1-F05	Type-N Male	SMA Male	5ft	DC to 18GHz	3.897dB	1.30:1	± 2.0°	±0.1dB	ConductRF Only
SF18G-N1SF-F05	Type-N Male	SMA Female	5ft	DC to 18GHz	3.897dB	1.30:1	± 2.0°	±0.1dB	ConductRF Only
SF27G-E1EF-1M0	3.5mm Male	3.5mm Female	1M	DC to 27GHz	3.467dB	1.30:1	± 4.0°	±0.2dB	N9910X-708
SF27G-EFEF-1M0	3.5mm Female	3.5mm Female	1M	DC to 27GHz	3.467dB	1.30:1	± 4.0°	±0.2dB	N9910X-709
SW50G-C1CF-1M0	2.4mm Male	2.4mm Female	1M	DC to 50GHz	6.210dB	1.30:1	± 8.0°	±0.5dB	N9910X-714
SW50G-CFCF-1M0	2.4mm Female	2.4mm Female	1M	DC to 50GHz	6.210dB	1.30:1	± 8.0°	±0.5dB	N9910X-715

Images for illustration only, Data subject to change

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Other Tools](#) category:

Click to view products by [CONDUCTRF](#) manufacturer:

Other Similar products are found below :

[CR-05FL7--150R](#) [CR-05FL7--698K](#) [899-2-KT46](#) [899-5-KT46](#) [CR-0AFL4--332K](#) [CR-12FP4--260R](#) [5718X-01PD-19RO](#)
[CRCW04021100FRT7](#) [CRCW04021961FRT7](#) [5800-0090](#) [CRCW04024021FRT7](#) [CRCW040254R9FRT7](#) [CRCW0603102JRT5](#) [59065-5](#) [00-8273-RDPP](#) [00-8729-WHPP](#) [593033](#) [593058](#) [593072](#) [593564100](#) [593575](#) [593591](#) [593593](#) [LTLA506SBLAMNBL](#) [CRCW08052740FRT1](#)
[LUC-012S070DSM](#) [LUC-018S070DSP](#) [599-2021-3-NME](#) [599-JJ-2021-03](#) [00-5080-YWPP](#) [5E4750/01-20R0-T/R](#) [LW1A-L1-GD](#) [LW1A-L1-GL](#) [LW1A-P1-GD](#) [LW1L-A1C10V-GL](#) [LW1L-M1C70-A](#) [0202-0173](#) [00-9089-RDPP](#) [CRCW2010331JR02](#) [01-1003W-8/32-10](#) [601-GP-08-KT39](#) [601-JJ-06](#) [601-SPB](#) [601YSY](#) [602-JJ-03](#) [602SPB](#) [602Z](#) [603-JJ-07-FP](#) [603-JJY-04](#) [604J](#)