



Accessories for Wireless products

RF magnet antenna 5db R-SMA plug-in connector straight 3.6 m

Material number: 1188987 (Material number old: 90598014)

Features/Options

- RF magnet antenna with straight R-SMA plug-in connector without ferrite core
- Suitable for SW915
- Cable length 3.6 m
- Ordering unit: 1 piece

Product image



Technical data

Frequency	824 - 960 MHz, 1.8 GHz / 1.9 GHz
Type	Magnet foot antenna
Impedance	50 Ohm
Gain	5 dB
Colour	black
Dimensions	Ø foot 77 mm, height approx. 660 mm
Cable	3.6 m RG58
Connector	R-SMA (male)
Weight	388 g

Errors and omissions excepted.

Arrangement of receiver and switch antenna



Optimum
mounting

Possible
mounting

Unsuitable
mounting

Note

Magnetic base antennae must be mounted on a metal plate of min. 250 x 250 mm size.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for ZF Cherry manufacturer:

Other Similar products are found below :

[0609-0801](#) [J82-16001LUNEU-0](#) [714-0262](#) [GPTBRH11](#) [AN920036](#) [PEEA3000](#) [G86-62401EUAEAA](#) [KBCV4400N](#) [WCHY-118](#) [AS201801](#)
[MX1A-11NN](#) [AFIK-5002](#) [JK-A0104EU-2](#) [STE-1188751RFSP](#) [STE-1189974RFIS](#) [STE-1189975RFIS](#) [STE-1225705RFGF](#) [STE-](#)
[1316916RFHB](#) [STE-1370677RFRX](#) [STE-1428116RF96](#) [E21-00A](#) [E34-00LV](#) [E63-00L](#) [GPSCRS11](#) [T10-01A](#) [T56-02M](#) [PHGA-3100](#)
[G813000LPNUS0](#) [G813512LADUS-0](#) [G836104LANUS](#) [0E1900A0](#) [0609-0756](#) [STE-1209282RF10](#) [STE-1362227RFRC](#) [DC3AA1LD](#) [E69-](#)
[00AA](#) [T56-12M](#) [D44CR1MD](#) [G836104LPNUS](#) [DC3C-M5RC](#) [STE-1373187RFRX](#) [WCHY-106](#) [0E6840A0](#) [G8011900LPMUS0](#) [PAAA3000](#)
[0E72-40HT](#) [G84-4700LUCUS-2](#) [G86-63400EUADAA](#) [STE-1042609RFRC](#) [STE-1190530RF95](#)