


Mounting Bases, Cable Ties and Accessories

Installs in-line with the wire bundle!


In-Line Mounting Base



BULK CAT. NO.	MOUNTING METHOD	WIDTH ACCOM. IN./MM	MAX. TIE		LENGTH IN./MM	BULK PKG. QTY.
			WIDTH IN./MM	LENGTH IN./MM		
TC815-TB	#10 screws	.30/7.62	.75/19.05	1.13/28.58	500	

A standard 2-hole base that installs in-line with the wire bundle that conceals it.
 • Natural nylon color.
 For use in temperatures ranging from -40° F to 185° F (-40° C to 85° C).

Miniature Base




BULK PKG. CAT. NO.	MOUNTING METHOD	MAX. TIE WIDTH ACCOM. IN./MM	LENGTH IN./MM	WIDTH IN./MM	MATERIAL	BULK PKG. QTY.

• Natural nylon color.
 For use in temperatures ranging from -40° F to 185° F (-40° C to 85° C).

Handles ties installed in either direction!

Low-Profile Four-Way Mounting Base




STD. PKG. CAT. NO.	BULK PKG. CAT. NO.	MOUNTING METHOD	MAXIMUM TIE WIDTH ACCOM. IN./MM	WIDTH IN./MM	LENGTH IN.	STD. PKG.	BULK PKG.
TC5828	TC828-TB*	#8 screw	.19	.39/9.91	.88/22.23	100	1,000

The TC826-TB mounting base can be used to tie bundles running parallel or perpendicular to length of base.
 The TC828-TB mounting plate also handles ties installed in either direction and is somewhat smaller than TC826.
 *Natural nylon color is standard. Replace TB with O suffix for black color.
 For use in temperatures ranging from -40° F to 185° F (-40° C to 85° C).

Firmly locks into position when projecting pin is pushed into the mounting hole.

Self-Riveting Base



BULK PKG. CAT. NO.	MOUNTING HOLE PKG. SIZE	MAX. TIE WIDTH ACCOM. IN./MM	WIDTH IN./MM	LENGTH IN./MM	MATERIAL	BULK PKG. QTY.
TC116-O	.146	.190	.5/12.7	.75/19.05	Nylon 6.6 (Black)	1,000
TC118-TB	.169	.190	.5/12.7	.75/19.05	Nylon 6.6 (Blue)	1,000
TC120	.196	.190	.5/12.7	.75/19.05	Nylon 6.6 (Yellow)	1,000

Slip tie under base to attach bundle.
 For use in temperatures ranging from -40° F to 185° F (-40° C to 85° C).

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [ABB manufacturer:](#)

Other Similar products are found below :

[TY27MX](#) [TV10-516R](#) [RF727](#) [2CMA100178R1000](#) [ACS150-01E-09A8-2](#) [KS70-1104](#) [A75-30-11-230V-50HZ](#) [10-100](#) [5SDD](#) [92Z0401](#)
[ESV14-BS](#) [EZS-21-250](#) [F204AC-40/0.1](#) [F362-25/0.03](#) [A40-30-10-84](#) [AF26-30-00-14](#) [AF30-30-00-13](#) [AF460-30-11-68](#) [AF50-30-11-70](#)
[1455](#) [B14-250](#) [EF45-30](#) [ERG297](#) [HSC2-20](#) [1SAM201904R1001](#) [1SAM350000R1003](#) [1SAZ711201R1045](#) [1SAZ721201R1009](#)
[1SAZ721201R1014](#) [1SAZ721201R1025](#) [1SAZ721201R1045](#) [1SBL367001R1300](#) [1SDA057197R1](#) [1SFA611100R1104](#) [1SFA611101R1002](#)
[1SFA611130R1103](#) [1SFA611133R1106](#) [1SFA611143R1101](#) [1SFA611202R1108](#) [1SFA611203R1108](#) [1SFA611210R1101](#)
[1SFA611215R1001](#) [1SFA611216R1108](#) [1SFA611281R1002](#) [1SFA611285R1002](#) [1SFA611702R6006](#) [1SFA616162R1025](#)
[1SFA896106R1100](#) [1SVR730020R0200](#) [IPC4111](#) [OHB125J12](#)