

# 169 MHz Antenna

## Key Features

- 169 MHz
- Bendable whip
- SMA/m connector

## Description



The AMB1930 is a robust antenna for 169 MHz applications. The antenna has a SMA/m connector. The antenna is equipped with a bendable whip.

Because of the antenna technology a ground plane is needed. The antenna is optimized to work with a square ground plane of 30 x 30 cm.



## Range of Application

The AMB1930 is well suited for all 169 MHz applications where good radio performance is needed as for example in metering applications.

## Specification

Part number	AMB1930
Frequency	169 MHz
VSWR	< 2:1
Gain	max. -2 dBi
Height	305 mm
Diameter	15 mm
Weight	43 g
Connector	SMA male
Temperature	-40 to +85°C
Ingress Protection	IP65

## Ordering Information

Item no.	Description
AMB1930	Antenna 169 MHz



**AMBER wireless GmbH**  
 Phone +49.651.993.550  
 Email [info@amber-wireless.de](mailto:info@amber-wireless.de)  
 Internet [www.amber-wireless.de](http://www.amber-wireless.de)

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [wurth manufacturer](#):*

Other Similar products are found below :

[687001](#) [742700](#) [74270062](#) [74437349220](#) [744741101](#) [750314624](#) [750341638](#) [31402](#) [686626050001](#) [744741471](#) [744772681](#) [744777](#)  
[749119950](#) [750312504](#) [890334025009](#) [IC-744885](#) [875115350002](#) [865230143004](#) [860160275030](#) [600690282801](#) [178050601](#) [615008138221](#)  
[750311898](#) [744999](#) [7446823003](#) [7446323004](#) [744028](#) [66201621822](#) [7446221012](#) [744720](#) [760895431](#) [760895651](#) [662006236022](#)  
[64900621822](#) [418117270910](#) [890334026014](#) [744839208072](#) [744762A/RFI](#) [74651174R](#) [744838180160](#) [750310346](#) [861011384014](#)  
[750817018](#) [3020903](#) [885342](#) [2603019321001](#) [2603019021001](#) [2606039021001](#) [2608019324001](#) [2607019213001](#)