



## Pushbutton switches

### 9050.4100

<b>Product number</b>	<b>9050.4100</b>	
<b>Business unit</b>	Switches, Sensors & Controls	
<b>Product family</b>	Pushbutton switches	
<b>Actuation type</b>	direct	
<b>Packing unit</b>		100
<b>ROHS conform</b>	yes	
<b>Output</b>	catalogue miniature switch	
<b>Switching function</b>	Changeover switch (SPDT momentary)	
<b>Material fixed contact</b>	Ag	
<b>Contact system</b>	Electrical life	2500
<b>Number of poles</b>	1 - pole	
<b>connections</b>	Solder terminal, sealed	
<b>Mechanical life endurance</b>		100000
<b>Rating IEC</b>	4 A 30 V DC	
	5 A 48 V AC	
<b>Contact resistance (new condition)</b>	< 20 mOhm	
<b>Insulation resistance (new condition)</b>	> 1000 MOhm	
<b>Voltage strength at 250 V</b>	small contact distance	> 1000 V
<b>Ambient temperature</b>	-25 °C ... +70 °C	
<b>Actuators and additional actuators</b>	actuator: CuZn chrome-plated	
<b>Housing description</b>	threaded socket: CuZn nickel-plated, hexagonal nuts of nickel-plated CuZn	
	toothed disc: Duroplast (base) / chromated galvanized steel (bracket plate)	
	bracket plate: stainless steel	
	base plate: DAP, olivegreen	
<b>Connection surface</b>	bearing connection	silver plated
	external connection	silver plated
<b>Contact material</b>	Ag	
<b>Contact type</b>	lifting contact	
<b>Operating force</b>	≤ 2.3 N	
<b>Miscellaneous</b>	smooth action version / stroke 1.1 mm / corresponding pushbuttons 9090.16.. see additional parts	
<b>Type of fastening</b>	central fastening M6 x 0.75	

Technical changes reserved. Dimensions are not binding.

Detailed specifications available on request.

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [marquardt](#) manufacturer:*

Other Similar products are found below :

[1661.0201-00](#) [2420.0101](#) [01050.5305-00](#) [01802.1108-02](#) [1264.3501](#) [1921.1101](#) [1045.2702](#) [1050.0151](#) [0320.0302](#) [3250.0590](#) [1800.1108](#)  
[01050.3102](#) [01835.3102-01](#) [2709.5101](#) [1552.3112](#) [1804.1102](#) [1839.1407](#) [840.000.071](#) [1824.1101](#) [1805.7109-03](#) [1263.0201](#) [1251.0106](#)  
[1363.0101](#) [1808.6302-00](#) [01805.7104](#) [1352.0101](#) [1935.3133](#) [828.000.021](#) [1269.0201](#) [02410.0401-02](#) [1010.0101](#) [1837.1118](#) [02410.0301-02](#)  
[02420.0101-00](#) [1005.0101](#) [2410.1001](#) [1552.4606](#) [2410.0301](#) [2410.0101](#) [01881.1104-01](#) [1832.8112](#) [1838.1509-01](#) [1010.7254](#) [01004.1002-02](#)  
[825.003.011](#) [1230.0501](#) [5000.0103](#) [09033.0400-00](#) [0100.1201](#) [0132.0101](#)