



ANSI Y14.5M-1982 APPLIES

THIS DRAWING COVERS A PROPRIETARY ITEM AND IS THE PROPERTY OF MICRO SWITCH, A DIVISION OF HONEYWELL. THIS DRAWING IS NOT TO BE COPIED OR USED WITHOUT THE APPROVAL OF MICRO SWITCH		THIRD ANGLE PROJECTION	
CHARACTERISTICS		ELECTRICAL DATA	
OPERATING FORCE - - - - - 6-12 LBS		CONTACT ARRANGEMENT	
FULL OVERTRAVEL FORCE - - - 30 LBS MAX		4X SPDT	
RELEASE FORCE - - - - - 4 LBS MIN		28 VDC	
PRETRAVEL - - - - - .070 MAX		LOAD	
DIFFERENTIAL TRAVEL - - - .020 MAX		SEA LEVEL	
OVERTRAVEL - - - - - .250 MIN		50,000 FT	
RES	7	RES	7
IND	4	IND	2.5
MOTOR	4	MOTOR	
		SCALE FULL	
		DO NOT SCALE PRINT	
		UNLESS OTHERWISE SPECIFIED TOLERANCES ARE	
		ONE PLACE (.0) ±.030	
		TWO PLACE (.00) ±.015	
		THREE PLACE (.000) ±.005	
		ANGLES ±	
		WEIGHT	

- NOTES**
- 1 - COINCIDENCE OF OPERATING AND RELEASING POINTS: .010 OF PLUNGER TRAVEL
 - 2 - CORROSION RESISTANT STEEL ENCLOSURE
 - 3 - SWITCH SEALED PER MIL-PRF-8805 SYMBOL 3
 - ④ CIRCUIT DIAGRAM, CATALOG LISTING, DATE CODE AND FED. MFG. CODE ARE SHOWN ON NAMEPLATE
 - ⑤ HARDWARE MAY BE PACKAGED UNASSEMBLED PER MIL-PRF-8805

CATALOG LISTING
ML-1008
PAGE 1 OF 1
RELEASE NO. PR-24160
REPLACES
ISSUE 1
CHECK
REVISIONS
CHECK
19 AUG 99
J A F
CHECK
19 AUG 99
G J W
DRAWN

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Basic / Snap Action Switches](#) category:

Click to view products by [Honeywell](#) manufacturer:

Other Similar products are found below :

[83228001](#) [01.098.1358.1](#) [602EN1-6B](#) [602EN532](#) [602EN535-RB](#) [602HE5-RB1](#) [604HE162](#) [604HE223-6B](#) [624HE17-RB](#) [6HM89](#) [6PA78-JM](#)
[6SE1](#) [6SX1-H58](#) [70500840](#) [MBD5B1](#) [MBH2731](#) [73-316-0012](#) [79211759](#) [79211923](#) [79218589](#) [7AS12](#) [ML-1155](#) [ML-1376](#) [831010C3.0](#)
[831060C3.TL](#) [831090C2.EL](#) [83131904](#) [84212012](#) [8AS239](#) [8HM73-3](#) [903VB1-PG](#) [914CE1-6G](#) [PL-100](#) [11SM1077-H4](#) [11SM1077-H58](#)
[11SM1-TN107](#) [11SM405](#) [11SM703-T](#) [11SM8423-H2](#) [11SX37-T](#) [11SX48-H58](#) [11SX55-H58](#) [11SM2442-T](#) [11SM76-T](#) [11SM77-H58](#)
[11SM77-T](#) [11SM863-T](#) [11SM866](#) [11SX47-H58](#) [A7CN-1M-1-LEFT](#)