



Neon Indicator Lamps

Configuration	Part Number	Old Ref. Number	Design Current mA	Maximum Breakdown Voltage	
				VAC	VDC
T-4 1/2 Candelabra Screw Base					
	B7 A	NE -45	2.0	65	90
	F3 A	NE -57	2.0	65	90
	F4 A	NE -58	2.0	65	90
	J2 A	AR -3	2.0	80	115
T-4 1/2 S.C. Bayonet Base					
	B6 A	NE -21	2.0	65	90
	B8 A	NE -47	2.0	65	90
T-4 1/2 D.C. Bayonet Base					
	B5 A	NE -17	2.0	65	90
	B9 A	NE -48	2.0	65	90
S-7 D.C. Bayonet Base					
	R1 A	NE -79	8.0	65	90

Footnotes

- | | | |
|--|---|---|
| <p>1. Life value is to approximately 50% of initial light output. Values shown apply to use on AC unless otherwise shown. Life on DC is approximately 60% of AC values when DC current is equal to RMS AC value. When equal DC and RMS AC voltages and equal</p> | <p>resistances are utilized, life will be approximately the same.</p> <p>2. For DC operation of high brightness lamps use a minimum of 150 circuit volts. Maximum initial breakdown voltage 95 VAC, 135 VDC in light.</p> | <p>3. Tinned leads.</p> <p>4. High brightness.</p> <p>5. Formed tip.</p> <p>6. Dark effect reduced.</p> <p>7. Lamp drops through a Ø.310" cylinder of .500" minimum length.</p> |
|--|---|---|

147 Central Avenue
 Hackensack, NJ 07601
 Phone: (201) 489-8989
 Fax: (201) 489-6911

18703 Dix Toledo Road
 Brownstown, MI 48193

Saret Zone Franca, Edificio B
 Alajuela Costa Rica

E-mail: sales@chml.com • Web Site: www.chml.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Lamps category](#):

Click to view products by [Visual Communications manufacturer](#):

Other Similar products are found below :

[5911-086-13](#) [5AB](#) [6180](#) [7009](#) [8623](#) [909](#) [912](#) [1224](#) [1230](#) [DE603](#) [BF20100-11B](#) [1892](#) [NL177WL2A](#) [NL276C2A](#) [IFL-LX2162-16T](#) [C2A-T](#)
[C9A](#) [301](#) [303](#) [SM2440L](#) [A1C](#) [A2B](#) [19](#) [268](#) [GT-NE6H1225T](#) [CM1820](#) [CM5004WW](#) [303](#) [32-2211T](#) [36EN-2113](#) [407](#) [4916S1](#) [521-7332](#)
[5314N1](#) [5314N2](#) [311](#) [WWT1-EW10/GRN](#) [4925H1](#) [DW07](#) [MS25231-313](#) [5603437](#) [5603851](#) [CM2](#) [7683EBP](#) [8553](#) [XE135B](#) [WWT2-](#)
[EW34BLA](#) [5705H7](#) [NL2951WL2G](#) [1301910036](#)