


600V , 20A , Trench-FS IGBT

Features

- ◆ Advanced Trench+FS (Field Stop) IGBT technology
- ◆ Low Collector-Emitter Saturation voltage, typical data is 1.7V @ 20A.
- ◆ Easy parallel switching capability due to positive Temperature coefficient in Vce.
- ◆ 10uS short-circuit SOA
- ◆ Fast switching
- ◆ High input impedance
- ◆ Pb- Free product
- ◆ Marking Code XNS20N60T



Schematic Diagram



TO-247

Applications

- ◆ General general-purpose inverter
- ◆ Motor control
- ◆ Intelligent power module.

Electrical characteristics(T_J = 25°C unless otherwise noted)

Symbol	Parameter	Test conditions	Units	Min.	Typ.	Max.
V _{(BR)CES}	Collector - Emitter breakdown voltage	V _{GE} = 0V, I _D =250uA	V	600	—	—
V _{CE(sat)}	Collector-Emitter Saturation voltage	V _{GE} =15V, I _C =20A,T _C =25°C	V	—	1.7	1.95
		V _{GE} =15V, I _C =20A,T _C =125°C	V	—	1.95	—
V _{GE(th)}	Gate threshold voltage	V _{GE} = V _{CE} , I _C = 0.25 mA	V	4.0	5.2	6.5
V _F	Diode Forward Voltage	I _F =20A	V	—	1.8	2.3
I _{GES}	Gate to Emitter Forward Leakage	V _{ge} =+30V	nA	—	—	200
I _{GESR}	Gate to Emitter reverse Leakage	V _{ge} =-30V		-200	—	—
I _{CES}	Zero gate voltage collector current	V _{CE} =600V	uA	—	—	25

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [IGBT Transistors](#) category:

Click to view products by [XINER](#) manufacturer:

Other Similar products are found below :

[748152A](#) [FGH60T65SHD_F155](#) [APT100GT60B2RG](#) [APT13GP120BG](#) [APT20GN60BG](#) [APT20GT60BRDQ1G](#) [APT25GN120B2DQ2G](#)
[APT35GA90BD15](#) [APT36GA60BD15](#) [APT40GP60B2DQ2G](#) [APT40GP90B2DQ2G](#) [APT50GN120B2G](#) [APT50GT60BRG](#)
[APT64GA90B2D30](#) [APT70GR120J](#) [NGTB10N60FG](#) [NGTB30N60L2WG](#) [NGTG25N120FL2WG](#) [IGP30N60H3XKSA1](#) [STGB15H60DF](#)
[STGFW20V60DF](#) [STGFW30V60DF](#) [STGFW40V60F](#) [STGWA25H120DF2](#) [FGB3236_F085](#) [APT25GN120BG](#) [APT25GR120S](#)
[APT30GN60BDQ2G](#) [APT30GN60BG](#) [APT30GP60BG](#) [APT30GS60BRDQ2G](#) [APT30N60BC6](#) [APT35GP120JDQ2](#) [APT36GA60B](#)
[APT45GR65B2DU30](#) [APT50GP60B2DQ2G](#) [APT68GA60B](#) [APT70GR65B](#) [APT70GR65B2SCD30](#) [GT50JR22\(STA1ES\)](#) [TIG058E8-TL-H](#)
[IDW40E65D2](#) [NGTB50N60L2WG](#) [STGB10H60DF](#) [STGB20V60F](#) [STGB40V60F](#) [STGFW80V60F](#) [IGW40N120H3FKSA1](#)
[RJH60D7BDPQ-E0#T2](#) [APT40GR120B](#)