


## 1200V , 40A , Trench-FS IGBT

### Features


- ◆ Advanced Trench +FS (Field Stop) IGBT technology
- ◆ Low Collector-Emitter Saturation voltage, typical data is 1.8V @ 40A.
- ◆ Short-Circuit withstand time-10uS
- ◆ Easy parallel switching capability due to positive Temperature coefficient in Vce.
- ◆ Fast switching
- ◆ High input impedance
- ◆ Pb- Free product



Schematic Diagram

### Applications

- ◆ Welding
- ◆ General purpose inverters
- ◆ Motor controls
- ◆ Induction Heating
- ◆ UPS



TO-264

### Electrical characteristics(T<sub>J</sub> = 25°C unless otherwise noted)

Symbol	Parameter	Test conditions	Units	Min.	Typ.	Max.
V <sub>(BR)CES</sub>	Collector - Emitter breakdown voltage	V <sub>GE</sub> = 0V, I <sub>D</sub> = 0.5mA	V	1200	—	—
V <sub>CE(sat)</sub>	Collector-Emitter Saturation voltage	V <sub>GE</sub> =15V, I <sub>C</sub> =40A, T <sub>C</sub> =25°C	V	—	1.8	2.3
		V <sub>GE</sub> =15V, I <sub>C</sub> =40A, T <sub>C</sub> =125°C	V	—	1.95	—
V <sub>GE(th)</sub>	Gate threshold voltage	V <sub>GE</sub> = V <sub>CE</sub> , I <sub>D</sub> = 0.4mA	V	4.0	5.2	6.5
V <sub>F</sub>	Diode Forward voltage	I <sub>C</sub> =40A	V	—	2.9	3.6
I <sub>GES</sub>	Gate to Emitter Forward Leakage	V <sub>ge</sub> =+30V	nA	—	—	200
I <sub>GESR</sub>	Gate to Emitter reverse Leakage	V <sub>ge</sub> =-30V		-200	—	—
I <sub>CES</sub>	Zero gate voltage collector current	V <sub>CE</sub> =1200V	uA	—	—	100

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [IGBT Transistors](#) category:*

*Click to view products by [XINER](#) manufacturer:*

Other Similar products are found below :

[748152A](#) [FGH60T65SHD\\_F155](#) [APT100GT60B2RG](#) [APT13GP120BG](#) [APT20GN60BG](#) [APT20GT60BRDQ1G](#) [APT25GN120B2DQ2G](#)  
[APT35GA90BD15](#) [APT36GA60BD15](#) [APT40GP60B2DQ2G](#) [APT40GP90B2DQ2G](#) [APT50GN120B2G](#) [APT50GT60BRG](#)  
[APT64GA90B2D30](#) [APT70GR120J](#) [NGTB10N60FG](#) [NGTB30N60L2WG](#) [NGTG25N120FL2WG](#) [IGP30N60H3XKSA1](#) [STGB15H60DF](#)  
[STGFW20V60DF](#) [STGFW30V60DF](#) [STGFW40V60F](#) [STGWA25H120DF2](#) [FGB3236\\_F085](#) [APT25GN120BG](#) [APT25GR120S](#)  
[APT30GN60BDQ2G](#) [APT30GN60BG](#) [APT30GP60BG](#) [APT30GS60BRDQ2G](#) [APT30N60BC6](#) [APT35GP120JDQ2](#) [APT36GA60B](#)  
[APT45GR65B2DU30](#) [APT50GP60B2DQ2G](#) [APT68GA60B](#) [APT70GR65B](#) [APT70GR65B2SCD30](#) [GT50JR22\(STA1ES\)](#) [TIG058E8-TL-H](#)  
[IDW40E65D2](#) [NGTB50N60L2WG](#) [STGB10H60DF](#) [STGB20V60F](#) [STGB40V60F](#) [STGFW80V60F](#) [IGW40N120H3FKSA1](#)  
[RJH60D7BDPQ-E0#T2](#) [APT40GR120B](#)