

Item no. 99901410

Connector type F-56-ALM 4.9/8.4
For cable Draka Coax 10 AD 10 S AL

Frequency Range	0.3 - 3000 MHz
Impedance (Nom.)	75 Ω
Amp. Rating (measured)	Cable data
(calculated)	Cable data
Transfer Impedance (CoMeT)	<2,5 mΩ/m @ 5-30MHz
	<0,1 mΩ/con. @ 5-30MHz
Shielding Effectiveness (CoMeT)	>130 dB @ 30-1000MHz
	>120 dB @ 1000-3000MHz



All tests performed using instruments calibrated in accordance to our ISO 9001 certification. Further technical specifications and installation instructions can be obtained on request.

Return Loss (IEC 61169-1)
(Rhode und Schwarz ZVB-8)

0.3 - 500 MHz
500 - 860 MHz
860 - 1000 MHz
1000 - 1750 MHz
1750 - 2150 MHz
2150 - 3000 MHz

	Better than	Typical
	-33 dB	-35,6 dB
	-31 dB	-34,3 dB
	-30 dB	-33,3 dB
	-29 dB	-31,9 dB
	-29 dB	-31,7 dB
	-29 dB	-31,7 dB

Insertion Loss Max.

0.3 - 500 MHz
500 - 860 MHz
860 - 1000 MHz
1000 - 1750 MHz
1750 - 2150 MHz
2150 - 3000 MHz

	Better than	Typical
	-0,06 dB	-0,01 dB
	-0,07 dB	-0,02 dB
	-0,07 dB	-0,02 dB
	-0,07 dB	-0,02 dB
	-0,07 dB	-0,02 dB
	-0,08 dB	-0,03 dB

Temperature

Installing
Operating
Storing

-5° to +50° C
-40° to +100° C
-40° to +100° C

Intermodulation

3rd Order (@2x100mW)

IM3	IP3-value
<-145 dBc	>+92 dBm

Inner Conductor Resistance

(@ 1 A DC)

Cable data

Sealing Test

(IEC IP-code)

-

Insulation Resistance

(@ 500 VDC)

Cable data

O-rings

--

Dielectric Strength

DC Test Voltage

Cable data

Base Material

Body Parts
Inner Conductor

Brass CuZn39Pb3
-

Max. Tensile Strength

Overall

>392 N
>40 Kgf

Plating

Body Parts
Inner Conductor

Nitin-6
-

Torsional Strength

(Connector / Cable)

* NATM

Insulators

-

Test performed by

Date of release

Søren B. Sørensen
March 10, 2011

Remarks

* Not Able To Measure(NATM): The cable starts to twist without the connector loosing its grip.

ISO 9001:2008 / ISO 14001 certified

Distributor:

Corning Cabelcon Aps, Industriparken 10, DK 4760 Vordingborg
Tel: +45 55 98 55 99 · Fax: + 45 55 98 55 04
E-mail: cabelcon@cabelcon.dk · www.cabelcon.dk

CABELCON
connectors

Form 041 rev 8

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Connectors / Coaxial Connectors](#) category:

Click to view products by [Cabelcon](#) manufacturer:

Other Similar products are found below :

[R125315120](#) [8915-1511-000](#) [89674-0827](#) [5916-1103-603](#) [0106-001-000](#) [6-0001-3](#) [6001-7071-019](#) [6002-7051-003](#) [6002-7551-202](#) [6059674-1](#) [619550-1](#) [630059-000](#) [M39012/25-0021](#) [M39012/79-3008](#) [M39030/3-01N](#) [M39030/3-03N](#) [M3933/25-29N](#) [M3933/25-36N](#) [6500-7071-046](#) [6501-1071-002](#) [M83723/72W24576](#) [M83723/72W2457N](#) [6769](#) [CX050L2AQ](#) [7002-1541-010](#) [7003-1572-002](#) [7004-1512-000](#) [7009-1511-004](#) [7010-1511-000](#) [7029-1511-060](#) [7101-1541-010](#) [7101-1571-002](#) [7105-1521-002](#) [7145-1521-002](#) [7209-1511-011](#) [7210-1511-012](#) [7210-1511-015](#) [7210-1511-019](#) [7210-1511-040](#) [7225-1512-050](#) [7242-1511-000](#) [73137-5015](#) [73216-2241](#) [73251-0111](#) [73251-0672](#) [73276-1501](#) [73366-0013](#) [73404-2300](#) [73413-6080](#) [734151610](#)